

Manual Addendum





The information in this document is subject to change without notice and does not represent a commitment on the part of Native Instruments GmbH. The software described by this document is subject to a License Agreement and may not be copied to other media. No part of this publication may be copied, reproduced or otherwise transmitted or recorded, for any purpose, without prior written permission by Native Instruments GmbH, hereinafter referred to as Native Instruments.

"Native Instruments", "NI" and associated logos are (registered) trademarks of Native Instruments GmbH.

Mac, Mac OS, GarageBand, Logic, iTunes and iPod are registered trademarks of Apple Inc., registered in the U.S. and other countries.

Windows, Windows Vista and DirectSound are registered trademarks of Microsoft Corporation in the United States and/or other countries.

All other trade marks are the property of their respective owners and use of them does not imply any affiliation with or endorsement by them.

Document authored by: Adam Hanley, Gwydion ap Dafydd

Software version: 5.9.2 (08/2014)

Special thanks to the Beta Test Team, who were invaluable not just in tracking down bugs, but in making this a better product.

#### NATIVE INSTRUMENTS GmbH

Schlesische Str. 29-30 D-10997 Berlin Germany www.native-instruments.de

#### **NATIVE INSTRUMENTS North America, Inc.**

6725 Sunset Boulevard 5th Floor Los Angeles, CA 90028 USA www.native-instruments.com

#### NATIVE INSTRUMENTS K.K.

YO Building 3F Jingumae 6-7-15, Shibuya-ku, Tokyo 150-0001 Japan www.native-instruments.co.jp

#### NATIVE INSTRUMENTS UK Limited

18 Phipp Street London EC2A 4NU UK www.native-instruments.com



© NATIVE INSTRUMENTS GmbH, 2014. All rights reserved.

# **Table of Contents**

1	What's	s New in	REAKTOR 5.9.2	8
	1.1	Dynamic	Automation Labels	8
		1.1.1	Adding and Deleting Parameter Name Entries	9
		1.1.2	Editing Parameter Name Entries	9
		1.1.3	Bulk List Actions	9
2	What's	s New in	REAKTOR 5.9.1	11
	2.1	Custom A	Automation Names and New Automation Module	11
		2.1.1	Custom Automation Names	11
		2.1.2	Automation Module	12
	2.2	Hardware	e Control Module	14
		2.2.1	Message Types	15
		2.2.2	Available Note Colors	17
	2.3	Mouse Ar	rea - Mouse Over Output	17
	2.4	Voice Info	o - Unison Min/Max Inputs	18
3	What's	s New in	REAKTOR 5.9	20
	3.1	Panelset	Updates	20
	3.2	Double-c	lick Control Behavior	20
	3.3	QuickBus	s Highlighting in Core Structures	21
	3.4	Dedicate	d Sample Map Menu in the Sample Map Editor	22
	3.5	Snapshot	t Updates	23
		3.5.1	Snapshot Tagging	23
		3.5.2	Default if Missing Option	23
	3.6	MASCHIN	IE 2 Integration	25
		3.6.1	Snapshot Visibility	25
		3.6.2	Defining the Sub-Bank Name	28
		3.6.3	Panelsets	29

4	What's	New in I	REAKTOR 5.8?	30
	4.1	OSC Setti	ngs	30
	4.2	OSC and I	VIDI Controller Handling	36
		4.2.1	Controller Mapping	36
		4.2.2	Updated Connect Tab	43
	4.3	New OSC	Array Modules	46
		4.3.1	OSC Receive Array	47
		4.3.2	OSC Send Array	47
	4.4	Other OSC	CImprovements	48
	4.5	Sample M	anagement	48
		4.5.1	The Sample Map Editor	49
		4.5.2	Sample List View	50
		4.5.3	Keymapping View	56
		4.5.4	Waveform View	58
	4.6	Updates t	o Mouse Controlled Elements	60
		4.6.1	Fine-tuning	60
		4.6.2	Other Updates	62
	4.7	Bookmark	Behavior for Screensets	62
	4.8	Updated S	Screenset Options	63
	4.9	Updated S	Sample Rate Settings	64
5	What's	New in I	REAKTOR 5.7?	65
	5.1	Compiled	Core Cell Code Cache	65
	5.2	Explicit Pl	ay and Edit Modes	66
		5.2.1	Play Mode	67
		5.2.2	Edit Mode	68
	5.3	Screenset	S	70
		5.3.1	Creating Screensets	71
		5.3.2	Deleting Screensets	71

		5.3.3	Navigating Screensets	. 71
	5.4	Universal	Wire Debugging Mode	. 72
	5.5	Layout ar	nd Transport Changes	. 72
6	What's	s New in	REAKTOR 5.6.2?	. 74
	6.1	Improved	Structure Navigation	. 75
		6.1.1	Breadcrumb Navigation	. 75
		6.1.2	Other Structure Navigation Improvements	. 80
	6.2	Improved	Object Manipulation	. 82
		6.2.1	Adding Objects with the Searchbox	. 82
		6.2.2	Other Structure Workflow Improvements	. 84
	6.3	Miscellar	neous Improvements	. 86
		6.3.1	XY Module	. 86
		6.3.2	64 Bit Support	. 88
		6.3.3	Browser Navigation	. 89
		6.3.4	Recorder Bar	. 91
		6.3.5	Supported Graphics Formats	. 91
	6.4	Snapshot	S	. 92
		6.4.1	Recalling Snapshots	. 93
		6.4.2	Adding and Removing Snapshots	. 96
		6.4.3	Renaming and Copying Snapshots	. 100
		6.4.4	Comparing Snapshots	. 101
		6.4.5	Morphing between Snapshots	. 103
		6.4.6	Randomizing Snapshots	. 106
		6.4.7	Snapshot Banks	. 109
		6.4.8	Defining Snapshot Behavior for Instruments	. 115
		6.4.9	Opening and Saving Presets	. 119
7	Keybo	ard Short	tcuts	. 122
	7.1	Changed	Keyboard Shortcuts	. 122

Q	Kovh	oard Shortcut Overview	124
	7.2	New keyboard Shortcuts	

# 1 What's New in REAKTOR 5.9.2

Welcome to REAKTOR 5.9.2! This manual addendum provides information about the new feature in this release: Dynamic Automation Labels.

## 1.1 Dynamic Automation Labels

The Automation Module (see  $\uparrow$ 2.1.2, Automation Module for more information) can now change its parameter label/name that is sent to the host during runtime, utilizing its new input port:

Sel (Select) - Events arriving at this input select one of the available list entries. This means the host gets a notification that the parameter name has changed on runtime.



The new Sel input port of the Automation module.

### 1.1.1 Adding and Deleting Parameter Name Entries

To define the parameter name entries:

- 1. Select the Automation Module and open its properties.
- 2. Click on the CONNECT tab.
- 3. In the Custom Parameter Names table, click the Add button to add an entry, or the Delete button to delete an entry from the list.

### 1.1.2 Editing Parameter Name Entries

Each entry has an index (#) and a value (Value) field:

- The **index** is automatically set as an integer, starting from 0 for the first entry.
- The **value** is the automation parameter label that is to be sent to the host.

To change a value :

Double-click on the text you wish to edit. Type the text you wish to be associated with the corresponding index.

The Sel input selects which entry from the list is used as the automation parameter label:

- If the Sel input is *not connected*, then entry *O* is used.
- If the list is *empty*, then the original default parameter label will be used (i.e. the module's name and its macro path).
- If the Sel input is *out of bounds*, then it is clipped to  $0 \rightarrow$  n-1, where n is number of items in the list.

### 1.1.3 Bulk List Actions

You can create and edit lists of automation parameter labels outside of REAKTOR, which will considerably speed up the process of creating and saving large lists. To open, save, or clear lists of automation parameter labels, use the Custom Parameter Names table's additional buttons.



Use the buttons highlighted above to open and save long lists of automation parameter labels.

(1) **Read from File**: Click this button to open a file selection dialog that allows you to select a plain text file. The list of automation parameter labels will be filled with the content of this file.



This action will replace any existing list content.

(2) **Save to File**: Click this button to open a file save dialog that allows you to save the current list of automation parameter labels as plain text file.

(3) Clear List: Click this button to clear the entire list of automation parameter labels.



The file format is plain ASCII text with one line per entry. An entry index number is not needed, as REAKTOR will create these numbers.

# 2 What's New in REAKTOR 5.9.1

Welcome to REAKTOR 5.9.1! This manual addendum provides information about new features, usability updates and improvements. Here is a brief overview of the most important changes and additions:

- 12.1, Custom Automation Names and New Automation Module
- ↑2.2, Hardware Control Module
- ↑2.2.2, Available Note Colors
- 12.4, Voice Info Unison Min/Max Inputs
- VST Support for 16 outputs

## 2.1 Custom Automation Names and New Automation Module

REAKTOR 5.9.1 introduces two new features that provide enhanced options for customizing automation strings:

- Custom Automation Names
- Automation Module

### 2.1.1 Custom Automation Names

Every control that sends automation data now has a new entry field into which you can enter a custom parameter name that is sent to the host.

A control's automation name was previously linked directly to the module name and the macro(s) it occupied. This behavior still remains by default, but can be overwritten in the following manner:

- 1. Select the control you wish to edit and open its properties
- 2. Click on the CONNECT tab. The AUTOMATION section is located at the bottom of this tab

3. Enter the name you wish to use for the control in the Custom Parameter Name text box.



Deleting the contents of this text box will return the control automation name to the original default name.

### 2.1.2 Automation Module

Sending and receiving automation data was always possible with the simple panel elements (like knobs and XY panels), but it was not possible to send data generated by other elements, like the Mouse Area module.

The Automation module allows you to send and receive data to and from a host without the need of a standard control.

The module also allows you to send custom lists as well as numeric values, allowing for more user-friendly automation displays.

▶ The Automation module is located in the Auxiliary section of the Built-in Module list.



The Automation Module

The inputs of the module are as follows:

- Tch (Touch) sends the touch-state of the parameter, in other words: this lets the host know whether or not the user is moving the connected control.
  - A value greater than 0 should be sent if the touch-state is active.
  - A value of 0 or less should be sent if the touch-state is inactive.

- Val (Value) sets the current value of the module to be sent when an event arrives at the Trig input.
- Trig (Trigger) an event at this input triggers a send of the value currently at the Val input. To send, the Tch input also needs to be set to active state. If Tch input is in inactive state, then this Trig input has no effect.

The module has a single output:

• Val - outputs the automation value received from the host.

### List Mode

In the module properties it is possible to select between Value and List modes of operation.

► The MODE setting is located in the FUNCTION tab of the module properties.



When List is selected, the module sends strings from a list, rather than the value at the Val input. The Val input is now used to select entries from the list.

The contents of the list can be set in the LIST ENTRIES section of the module properties.



The Default List Entries

Here you can Add and Delete entries in a manner similar to the List module.

Each entry has an index (#) and a Value:

- The index is automatically set as an integer, starting from 0 for the first entry.
- The value is the text that is to be sent to the host.

To change a Value:

- 1. Double-click on the text you wish to edit.
- 2. Type the text you wish to be associated with the corresponding index.

### 2.2 Hardware Control Module

The Hardware Control module allows greater integration with NATIVE INSTRUMENTS hardware products. The module is designed to be updated with any new hardware NATIVE INSTRUMENTS MENTS might release in the future.

At the time of writing, this module allows custom control over certain features of the KOM-PLETE KONTROL S-SERIES hardware. ► The Hardware Control module is located in the *Terminal* section of the *Built-in Module* list.



The Hardware Control Module

The Hardware Control module has four inputs:

- Msg (Message Type) selects the message type to be sent by the module.
- Idx (Index) sets the index of the array into which data is to be written.
- W (Write) writes a value into the currently selected array index.
- Trig (Trigger) triggers the contents of the module's array.

REAKTOR must be used as a plug-in in the MASCHINE or KOMPLETE KONTROL software in order for the Hardware Control messages to be sent. Hardware Control messages are not sent when REAKTOR is used in stand-alone mode.

### 2.2.1 Message Types

Message Type	Msg Input Value
Set single note attributes	10
Set 128 note colors	11
Set note pressed support	40

#### **Set Single Note Attributes**

For this message type, the first index of the array (index 0) sets the MIDI note number, and the following indices are used to set various attributes for that note:

Hardware Control Module

Array[0]	Array[1]	Array[2]	Array[3]
MIDI Note Number	Note Color	Pressed State (0 or 1)	Note Type (O or 1)
0 127	0 17	0: Unpressed	0: Default
		1: Pressed	1: Control

The Note Type tells KOMPLETE KONTROL whether this is a standard playable note, or whether it's a control note used for special functions in instruments. Control notes will be excluded from performance functions, like the arpeggiator, in KOMPLETE KONTROL.



Sending any value outside of the value ranges specified above will cause the message to be ignored, and the relative setting will remain unchanged.



The pressed state will only be sent if Note Pressed Support is set to be active.

#### Set 128 Note Colors

This message type allows you to send the note colors for all MIDI notes in a single array. With this message type, the array index represents the MIDI note, and the value of that index sets the note color.

Array[0]	Array[1]	 Array[126]	Array[127]
MIDI Note 0 Color	MIDI Note 1 Color	 MIDI Note 126 Col-	MIDI Note 127 Col-
(017)	(0 17)	or (0 17)	or (0 17)

#### Set Note Pressed Support

A value of 40 at the Msg input sets the module to send the Note Pressed Support state. A single yes/no (0/1) value is needed, and is sent in array index 0:

- 0: No REAKTOR will not send Note Pressed messages; this is to be handled by the host.
- 1: Yes REAKTOR will send Note Pressed messages, taking control of this from the host.

### 2.2.2 Available Note Colors

Value	Color
0	Red
1	Orange
2	Light Orange
3	Warm Yellow
4	Yellow
5	Lime
6	Green
7	Mint
8	Cyan
9	Turquoise
10	Blue
11	Plum
12	Violet
13	Purple
14	Magenta
15	Fuchsia
16	Default
17	Inactive

If you send a note color value outside of the 0 to 17 range, the message will be ignored and the previous note color will not change.

### 2.3 Mouse Area - Mouse Over Output

The Mouse Area module has been updated to include a new output: MO (Mouse Over).



The Mouse Area Module

This output allows you to sense whether or not the mouse cursor is hovering over the Mouse Area on the panel.

- An event is sent each time the state changes.
- The event has a value of 1 when the mouse cursor is in the Mouse Area.
- The event has a value of 0 when the mouse cursor is not in the Mouse Area.

You can access the mouse position when the mouse cursor is hovering of the Mouse Area by using the PX and PY outputs, and checking the Always send PX and PY events option in the Mouse Area properties.

### 2.4 Voice Info - Unison Min/Max Inputs

The Voice Info module has been updated to include two inputs:

- Min sets the minimum unison voices for the instrument.
- Max sets the maximum unison voices for the instrument.



The Voice Info Module

These inputs mimic, and are connected to, the Unison options in the instrument properties.

If nothing is connected to these inputs, the settings in the instrument properties will be used, otherwise, the values at these inputs will be used.

# 3 What's New in REAKTOR 5.9

Welcome to REAKTOR 5.9! This manual addendum provides information about new features, usability updates and improvements. Here is a brief overview of the most important changes and additions:

- ↑3.1, Panelset Updates
- †3.3, QuickBus Highlighting in Core Structures
- †3.4, Dedicated Sample Map Menu in the Sample Map Editor
- †3.5, Snapshot Updates
- ↑3.6, MASCHINE 2 Integration

# 3.1 Panelset Updates

REAKTOR 5.9 features two improvements to the Panelsets:

- Panelsets can now be accessed when in Play Mode.
- The header visibility state of an instrument/ensemble is saved in the Panelset.

Panelsets are also part of the improved MASCHINE integration.

# 3.2 Double-click Control Behavior

Double-click behavior has been refined to have two different functions depending on whether or not Edit Mode is active:

- When in Edit Mode: double-clicking on a control will open the control's properties.
- When in Play Mode: double-clicking on a control will set that control to the default value.

# **3.3 QuickBus Highlighting in Core Structures**

To make it easier to navigate and edit Core structures, QuickBus highlighting has been added.

When you select any QuickBus connection, all connections to that same QuickBus will be underlined.



QuickBus highlighting of the Sens variable in a core structure using many QuickBuses.

When you click on any module or macro with QuickBus connections, all connections to the relevant QuickBuses will be highlighted in the same manner.



The same structure as before, but with one of the AHD macros selected.

# 3.4 Dedicated Sample Map Menu in the Sample Map Editor

To make using Sample Maps in REAKTOR more intuitive, the Sample Map import and export commands have been moved to a dedicated Sample Map menu.

The menu is located above the Sample Map list.

Sampler 🔫 🖛	•		Sample Map 🛛 👻	Map	Wa
Name	Root	L	Import (Merge)		tro
Clap Monstrosities 01	0	0	Import (Replace)	45	
Combo Monstrosities	1	1	Export including Audio	o Data	
Kick Monstrosities 01 1	2	2	Export with Reference	es Only	
				85 <sup>1</sup> /	

The Sample Map Menu

The Sample Map menu contains the following commands:

- *Import (Merge)* ...: opens a dialog window to load a Sample Map file and merge it with the currently loaded Sample Map.
- *Import (Replace) ...*: opens a dialog window to load a Sample Map file to replace the currently loaded Sample Map.
- *Export including Audio Data ...*: opens a dialog window to save the current Sample Map with all the relevant audio data embedded in the file.
- *Export with References Only* ...: opens a dialog window to save the current Sample Map without any embedded audio, but with references to files on your hard drive.

# 3.5 Snapshot Updates

### 3.5.1 Snapshot Tagging

As part of the improved MASCHINE integration, the snapshot interface and features have been updated. For more information on Snapshot tagging, please refer to section  $\uparrow$ 3.6, MASCHINE 2 Integration.

### 3.5.2 Default if Missing Option

Any modules that store data in a Snapshot (for example: knobs, lists, snap value, etc.) now have a new option in the SNAPSHOT section of the FUNCTION properties: Default if Missing.

P		Ô		$\mathbf{\nabla}$	
Attack		_		Fader 🔳	
FUNCTIO	N	INFO	VIEW	CONNECT	
RANGE					
Max			Stepsize		
	7			1	
Min	Min 0		Mouse Resolution		
			127		
Default			Fine-tuning Factor		
	4		10		
SNAPSH	отs				
ID for Files					
40			Snap Isolate		
			Defa	ult if Missing n/Rnd Isolate	

The Default if Missing checkbox

If you have created an ensemble and saved a number of Snapshots, then added extra controls to the ensemble after these Snapshots were generated, this control specifies how this module will react to Snapshot recall.

- When checked: if the loaded Snapshot does not contain specific information for the module, and the Snap Isolate property is unchecked, it will reset to the default value as specified in its properties.
- When **unchecked**: if the loaded Snapshot does not contain specific information for the module, it will remain at the last specified value (ie, a Snapshot recall will not change the value of the module).
- If the loaded Snapshot does contain data for the module, it will set the value of the module as expected.
- The behavior is slightly different when used in a host:
- When **checked**: loading a host project with no value for the control will cause it to reset to default, regardless of the Snap Isolate setting.
- In all other cases, the behavior is the same.

Any ensembles created before REAKTOR 5.9 will have the Default if Missing option unchecked for all relevant modules.

## 3.6 MASCHINE 2 Integration

The following chapter will cover the new features that relate to integrating your REAKTOR ensembles into MASCHINE 2's browser.

### 3.6.1 Snapshot Visibility

When using REAKTOR, you can browse for a number of different things: ensembles, modules, Snapshots, etc. Generally a Snapshot is considered to be a REAKTOR sound preset.

Since the MASCHINE Browser is used primarily to navigate sounds, it has been designed to scan for Snapshots within a REAKTOR Ensemble file. However, Snapshots need to be tagged in a way so that MASCHINE can integrate them in a sensible way.

#### **Tagging Snapshots**

Since a REAKTOR ensemble can be an instrument, an effect, or even both, we need to communicate which of these the Snapshot is classed as so MASCHINE will know where to place it in the Browser.

Tagging is done in the Snapshot window.

► To display Snapshot tags, enter the Edit menu and select *Show Meta Info*.



→ A new column will appear in the Snapshot browser displaying any tags applied to the Snapshots and Banks.

There are four kinds of tags:

- None: the sound will be hidden from the MASCHINE browser.
- Inst: an *Instrument* sound. Any Snapshot that generates audio, but does not alter incoming audio should be tagged as an *Instrument* sound.
- FX: an *Effect* sound. Any Snapshot that relies on, alters, or reacts to incoming audio should be tagged as an *Effect* sound.
- Both: a sound that can be either an Instrument or Effect. Any Snapshot that generates audio independently, but can also react to incoming audio somehow, should be tagged as *Both*.

### **Tagging a Single Snapshot**

- 1. Right-click on the Snapshot in the Snapshot browser.
- 2. Navigate to *NI Meta Info* to display the available tags.

3. Select the relevant tag for the Snapshot.



### **Tagging a Snapshot Bank**

Tagging a Snapshot bank will tag all Snapshots contained in that Bank with the same setting.

- 1. Right-click on the Bank name in the browser.
- 2. Navigate to *NI Meta Info* to display the available tags.
- 3. Select the relevant tag for the Snapshot.





After tagging, be sure to save the Ensemble file to make the changes permanent.

### **Single Preset Files**

If you save a preset file in REAKTOR - by using the *Save Preset As...* command in the File menu - the saved file will take the tag information from the last selected Snapshot.

If the Snapshot had no tag, you can tag it by using the Snapshot menu in REAKTOR's toolbar:

1. Right-click on the Snapshot menu.

2. Select the tag you wish to use.



3. Re-save the preset file.

Tagging a preset using this method will not change the tag of the original Snapshot.

### 3.6.2 Defining the Sub-Bank Name

Any ensemble created in REAKTOR and tagged to be found in MASCHINE 2's Browser will be automatically located in the REAKTOR bank.

In order to make locating the sounds easier, you can define a Sub-Bank name.

The Sub-Bank name is automatically taken from the name of the ensemble's Snapshot Master.

### **Changing the Snapshot Master**

By default, the Snapshot Master is the ensemble itself. However it is possible to change it to any instrument in the ensemble.

To change the Snapshot Master:

- 1. Select the instrument you wish to be the new Snapshot Master.
- 2. Enter the instrument's properties and navigate to the FUNCTION tab.
- 3. Toward the end of the function properties, there is a section labeled SNAPSHOT.
- 4. In this section, activate the Set As Master button.

SNAPSHOT	
ID for Files	
1	Snap Isolate
Set As Master	✓ Recall by MIDI

 $\rightarrow$  The selected instrument is now the Snapshot Master for the ensemble.

### 3.6.3 Panelsets

Even if no action is taken, your REAKTOR ensemble's interface will appear in the MA-SCHINE 2 interface when a sound from it is loaded. The appearance will be the same as the last saved state.

However, it is possible to make some optimizations to make using your ensemble in MA-SCHINE 2 a better experience.

#### **Default and Additional Views**

MASCHINE 2 has two ways of viewing a REAKTOR ensemble's interface:

- Default View
- Additional View

These views are taken automatically from the ensemble's Panelsets.

In order for MASCHINE 2 to recognize a Default and Additional view, you need to create two Panelsets:

- The first Panelset will be the first view displayed the Default View.
- The second Panelset will be the alternate view the Additional View.

Any further Panelsets will not be recognized by MASCHINE, though they will not interfere with the MASCHINE integration.

# 4 What's New in REAKTOR 5.8?

Welcome to REAKTOR 5.8! This manual addendum provides information about new features, usability updates and improvements. Here is a brief overview of the most important changes and additions:

- 14.2, OSC and MIDI Controller Handling
- ↑4.3, New OSC Array Modules
- <sup>†</sup>4.4, Other OSC Improvements
- <sup>†</sup>4.5, Sample Management
- 14.6, Updates to Mouse Controlled Elements
- 14.7, Bookmark Behavior for Screensets
- ↑4.8, Updated Screenset Options

# 4.1 OSC Settings

The OSC Settings window has been updated for better clarity and ease of use.

▶ To open the OSC Settings window, enter the File menu and select OSC Settings...

SC Activate								
OSC Receive	OSC Send	OSC Sync						
Receive on Port 10000		I	Local IP Addresse 192.168.222.1 10.1.72.77	es 25 (WLAN)				
Incoming OSC Monitor				Clear				
				Close				

OSC Settings window (OSC Receive tab)

If you have used the OSC Settings before, you will have noticed that the OSC Settings window now uses tabs to navigate between the different sections:

- OSC Receive: Set up communication from an OSC Device to REAKTOR here.
- OSC Send: Set up communication from REAKTOR to other OSC Devices here.
- OSC Sync: Contains the OSC sync options.
- ► In order to use OSC in REAKTOR, check the global OSC Activate check box in the top left corner of the OSC Settings window.

### **OSC Receive**

Receive on Port	Local IP Addresses
10000	192.168.222.25 (WLAN)
	10.1.72.77

OSC Receive Main Settings

The OSC Receive tab contains three main areas:

To the **top left** is the Receive on Port value display. This is where you can view or edit REAK-TOR's OSC input Port number.

► To change the Port number, double-click on the value displayed, and enter a new value.



The Port number is important for use in setting up communication from your OSC device.

To the **top right** you will see a display of the Local IP Addresses currently accessed by REAK-TOR. These addresses are not editable from REAKTOR, but are displayed for use in setting up your OSC device.

The large area at the bottom of the window is the Incoming OSC Monitor.

coming OSC Mor	itor	Clear
11:49:24.382	/1/n4next/a 0.686681	
11:49:24.382	/1/n4next/d 0.866388	
11:49:24.382	/1/n1next/a 0.0387935	
11:49:24.382	/1/n1next/d 0.197926	
11:49:24.383	/1/peri 0.568334	
11:49:24.383	/1/n1/l 0.969321	
11:49:24.383	/1/n1/y 0.426272	

OSC Monitor

This displays all of the incoming OSC messages received by REAKTOR, and is primarily used for checking your connection is working correctly.

To clear the monitor contents, click on the Clear button to the top right of the monitor display.

### **OSC Send**

OSC Activate				
OSC Receive	OSC Send	OSC Syr	nc	
OSC Targets				
Identifier		IP Address		Port
	_			
New	Scan			Remove
Name for this instance				Test Message
Reaktor5-164				
				Close

OSC Send Settings

This area is used for entering the information of your OSC device(s) to enable communication from REAKTOR to the device(s).

To enter the OSC target's information:

- 1. First, click on the New button below the OSC Targets window. A new target will then appear in the window with default information.
- 2. Enter the relevant information into the fields by clicking on the field and typing the correct settings from your OSC device.

3. When all the information is all entered correctly, if your OSC device has an incoming OSC indicator, you can send a test message by clicking the Test button. The test message will be sent out to all of the OSC targets in the list.



#### To automatically search for other OSC enabled instances of REAKTOR:

- 1. Click the Scan button. REAKTOR will send a 'ping' message and listen for a 'pong.'
- 2. A list of devices that sent a 'pong' reply to REAKTOR will appear in the OSC Targets list. Remove any targets that you do not wish to use by clicking on the target name in the list to select it, then click the Remove button to remove them.



Note that Scan only scans between port ranges 10000 and 10015.

### OSC Sync

SC Activate			
OSC Receive	OSC Send	OSC Sync	
No Sync	44		
Enable Sync as P	lave		Sync Signal Indicator
			Close

OSC Sync Settings

The OSC Sync tab contains three main options for how REAKTOR should use OSC Sync messages:

- No Sync: REAKTOR will not send, nor will it respond to, OSC Sync messages.
- Enable Sync as Master: REAKTOR will send OSC Sync messages to any device connected in the OSC Send tab.
- Enable Sync as Slave: REAKTOR will slave to OSC Sync messages sent from any device connected in the OSC Receive tab.

If either of the last two options is selected, two more options will be visible in the Select Sync Type: box.

No Sync	
<ul> <li>Enable Sync as Master</li> </ul>	
Enable Sync as Slave	Sync Signal Indicator 🛛 🔵
Select Sync Type:	
Time Sync 💿 Clock Sync	

OSC Sync Type Options

These options allow you to select the type of OSC Sync messages to be used:

- Time Sync: sends/receives transport messages (start/stop/continue) as well as tempo information.
- Clock Sync: sends/receives transport messages only.

## 4.2 OSC and MIDI Controller Handling

REAKTOR 5.8 introduces a new CONTROLLERS tab to the side pane, from which you can easily manage, edit and assign connections from both MIDI and OSC devices. The CONTROLLERS tab is also available in Play Mode, allowing you to assign MIDI and OSC connections without editing the ensemble structure.



When using REAKTOR as a plug-in, the controller assignments made in the CONTROL-LERS tab are saved along with the host project.

The CONNECT tab for panel elements has also been updated for improved usability. For details see  $\uparrow$ 4.2.2, Updated Connect Tab.

### 4.2.1 Controller Mapping

The CONTROLLERS tab shares the PANELSETS tab of the side pane.
_ ۵	Ô	I∔1	$\square$
CONTROLL	ERS	PAN	IELSETS
MIDI	0	ISC	
Control	Ch	Target	
🔶 CC 16	1	2-Osc:A	
💠 CC 16	1	2-Osc:A	
🔶 CC 16		2-Osc:A	
			I
			I
			——II
			——II
			I
			I
			—— II
Auto			

The Controller Mapping Pane

► In Edit Mode, use the CONTROLS and PANELSETS sub-tabs to switch between the Controller Mapping and the Panelsets panes.



In Play Mode, the Panelsets are not accessible from this tab, and so the sub-tabs will not be visible.

At the top of the Controller Mapping pane are two tabs, one for viewing and managing MIDI connections, and the other for viewing and managing OSC connections. These tabs are labeled MIDI and OSC respectively.

- ► To view the list of relevant current connections and recently used messages, click on either tab. Connections and messages will be displayed:
  - The current connections appear at the top of the list (they will be identifiable by the information present in the Target column).
  - Recently received messages appear below the current connections (by default, this list will only be refreshed each time you open the tab).
  - For MIDI, controller messages will appear above note messages.
- To view incoming messages in real-time, activate the Auto button below the list. Not only will this re-populate the list in real-time, but it will also highlight currently used messages.

Control	Target
↓ /1/n1/touch	
1/n1next/a	
/1/n1next/d	
<⊳ /1/n2/l	
<	
<⊳ /1/n2/y	
<⊳ /1/n2next/a	
<⊳ /1/n2next/d	

OSC Messages are highlighted as they are received.

## Filtering the List by Controller Data Type

► To filter the list of controller messages by data type, right-click (Mac OS X: [CTRL] + click) the Control column's header and select the data type from the context menu:

- All: Select this entry to see all MIDI message types.
- CC: Select this entry to see only MIDI CC (Continuous Controller) data.
- Note: Select this entry to see only MIDI Note data.
- *AT*: Select this entry to see only MIDI Aftertouch data.



The Control (Controller Data) context menu of the Controller Mapping pane

#### Filtering the Controller List by MIDI Channel

► To filter the list of controller messages by MIDI channel, right-click (Mac OS X: [CTRL] + click) the Ch (Channel) column's header and select the MIDI channel from the context menu.



The Ch (Channel) context menu of the Controller Mapping pane

### Filtering the Controller List by Ensemble or Instrument

► To filter the list of controller messages by Ensemble or Instrument, right-click (Mac OS X: [CTRL] + click) the Target column's header and select the ensemble or instrument from the context menu.



The context menu will be populated depending on the currently loaded Ensemble or Instrument.



The Target context menu of the Controller Mapping pane

## **Clearing Unmapped Controller Data from the Controller List**

► To clear unmapped data from the controller list, click on the Clear List Button, located at the bottom of the Controller Mapping pane.



The Clear List button in the Controller Mapping pane

### **Assigning and Deleting Controller Assignments**

► To assign MIDI and OSC controllers from this pane, drag the controller's entry from the list to the control you wish to connect to within REAKTOR.



Dragging a controller's list entry to an Instrument's control

To delete an assignment you can either:

- Select the relevant controller from the list and press the Delete key on your computer keyboard, or
- Select the controller from the list and click on the Remove Assignment button (garbage can icon) below the list.



The Remove Assignment button (garbage can icon)

#### Assigning Controllers through MIDI/OSC Learn

To the top right of the Controller Mapping pane, you will find the re-located MIDI Learn button, which now also functions as an OSC Learn button. This allows you to use MIDI/OSC Learn in Play Mode.

To connect a MIDI/OSC controller to a REAKTOR control using the MIDI/OSC Learn button:

- 1. Click on the MIDI/OSC Learn button to activate MIDI/OSC Learn mode.
- 2. Click on the control you wish to connect to in the REAKTOR interface.
- Move the controller on your MIDI or OSC device that you wish to connect to the control in REAKTOR
- $\rightarrow$  The connection should now be made and will be visible in the Controller Mapping list.

## 4.2.2 Updated Connect Tab

The MIDI and OSC connection settings within the module properties have been updated to be easier to use and more clearly laid out.

To access the MIDI and OSC connection settings, click on the CONNECT tab in a control's properties.

In the MIDI and OSC Connections area you will see three tabs:

- MIDI: This is where you can access the controls to set up a MIDI control and/or MIDI output for a control. The properties of this area remain as they were in previous REAKTOR versions.
- OSC RCV (OSC Receive): In this tab you will find the options for connecting an OSC source to control the REAKTOR module.
- OSC SEND: This tab contains the settings for sending OSC messages from the module to another OSC device.



In order for the OSC settings to function correctly, you must first set up the OSC properties in the OSC Settings window.

## **OSC** Receive

Pitch			Fader 🗈							
FUNCTION	CONNECT									
MIDI & OSC CONNECTIONS										
	MIDI OSC RCV OSC									
Address Pa	ttern	Inc	dex III							
Add Source	•									

**OSC Receive Connection Settings** 

The main area of the OSC RCV (OSC Receive) tab displays a list of currently connected OSC sources and, where applicable, the parameter index number.

To add a new OSC source to the list:

- 1. Click on the Add Source drop-down menu.
- 2. Select the *New...* entry, and then type the name of the OSC Address.



 $\rightarrow$  The newly created OSC source will be added to the list of controllers.

To add an OSC source from a list of recently received OSC controllers:

1. Click on the Add Source drop-down menu.

2. Select the *Recently Received* entry, and then select one of the options available.



 $\rightarrow$  The selected OSC source will be added to the list of controllers.



You can clear the *Recently Received* list by using the *Clear Recent List* option in the Add Source menu.

To delete an Address Pattern, select the Address you wish to delete in the list and either

- ▶ press the Delete key on your computer keyboard, or
- click on the Delete Source button (garbage can icon) to the right of the list.

## **OSC Send**

Pitch			Fade	r 🖻			
FUNCTION	INFO	CON	NECT				
MIDI & OSC	CONNEC	TIONS					
		OSC RCV OSC					
ldentifier							
Add Target Send Address /Pitch	<b>▼</b> Pattern						

OSC Send Connection Settings

The OSC SEND tab's main area is a list of currently connected Targets (OSC devices).

#### $\mathsf{To}$ define the OSC Target to which the OSC message will be sent:

The Add Target drop-down menu below the list will be populated with Identifiers set up in the OSC Settings. Select the OSC Identifier's entry from the Add Target drop-down menu.

The Address Pattern of the OSC message sent from the control can be entered manually in the Send Address Pattern field. By default, the Send Address Pattern is based on the name of the control.

# 4.3 New OSC Array Modules

REAKTOR 5.8 adds two new built-in modules: **OSC Receive Array** and **OSC Send Array**. Both of these modules can be found in the *Terminal* category, along with the other OSC modules.

## 4.3.1 OSC Receive Array



The OSC Receive Array Module

The **OSC Receive Array** module (OSC Rcv Array) is designed to be used with any OSC message that is sent in an array format, using indices. A maximum of 128 array elements is supported.

In order for the OSC Receive Array module to work correctly, you need to add an OSC source in the CONNECT tab using the method covered in section  $\uparrow$ 4.2.2, Updated Connect Tab.

When a message is received by this module, the following values are sent from the 4 ports:

- The N port sends the number of received elements.
- The Gate port sends a value of 1.0.
- For each element the Idx port sends the index number (0 to N-1), and the Out port sends the value of the array element at [Idx].
- Finally, when all of the data is sent from the Idx and Out ports, the Gate output sends a value of O.

## 4.3.2 OSC Send Array

• N	
• Trig	
• ld×	
• W	
OSC Send Array	

The OSC Send Array Module

The **OSC Send Array** module sends OSC messages using an indexed array of parameters. A maximum of 128 array elements is supported.

In order for the OSC Receive Array module to work correctly, you need to add an OSC target in the CONNECT tab using the method covered in section  $\uparrow$ 4.2.2, Updated Connect Tab.

- Parameter values are written into the array using the Idx and W inputs.
- The N input determines how many parameters will be sent. If the N input is not connected, or is set to zero, all of the parameters in the array will be sent.
- The message is sent when an event is received at the Trig input.

## 4.4 Other OSC Improvements

REAKTOR 5.8 also includes the following OSC improvements:

- OSC is now enabled when REAKTOR is used as a plug-in.
- The MIDI activity meters have been updated to also display OSC activity.
- Limits on the total number of OSC connections have been removed.
- The maximum number of ports for the OSC Send and OSC Receive modules has been increased to 40.

# 4.5 Sample Management

REAKTOR 5.8 includes two major updates to sample management:

- Samples and Sample Maps can now be edited in Play Mode.
- The embedding of samples in the ensemble is now a property of the sample itself.

## **Moved Controls**

These updates include many smaller updates, including usability changes:

• The **preferences of the Sample Map Editor itself**, i.e. the editing and pre-listen preferences, are now in the far right-hand corner settings menu.



• The **Prelisten button (loudspeaker icon)** is now in the Sample Info bar above the Sample Map/Waveform display.

METALs.wav	44100 Hz	1.86 s
0.0 xs ' ' '   0.6s ' ' '   1.2s ' '   1.2s ' '		1.7s 👘 🔶

## 4.5.1 The Sample Map Editor

One of the first changes you may notice is that now, because the Sample Map Editor is available in Play Mode, the button used to access it has moved to the main tool bar at the top of the interface, beside the Player/Recorder and the Info Hints buttons.



The new location of the Sample Map Editor button.

#### To open the Sample Map Editor either:

- ▶ Click on the Sample Map Editor button mentioned above, or
- ▶ Press [F9] on your computer keyboard.

Sample Management

	Root			LVel	HVel E			BAUCH2.way	44100 Hz	
814200021	71	71	71	•	127			127		
8101200021				-	127	<u> </u>		UUS DNL MAPPEZL HLURYS AD		
AZ-CLAP	76	76	76	0	127		[C:\REMMER\			
BAUCH2	75	75	75	0	127		[C:\REMMER\			
Buegelterfal	64	64	64	0	127	$\checkmark$	[C:\REMMER\	55   ; • 6_ TEDUUD28; T_ • DU		
CLAP_LOP	77	77	77		127	$\checkmark$	[C:\REMMER\	ttsHRDR2L_IPDD≥IDIstR >>>>>>>>>>>>>>>>>>>>>>>>>>>>>>>>>>>>		
CLDISTOM3	69	69	69	0	127	$\checkmark$	[C:\REMMER\		C6 C7	
CONG_SHAK	67	67	67	0	127	$\checkmark$	[C:\REMMER\			
CYMBAL	82	82	82	0	127	$\checkmark$	[C:\REMMER\ 🗸			ΤL
								4		
								Root Low High LVel HVel	<b>Tune</b> Gain	

The Sample Map Editor

The Sample Map Editor is divided into two halves:

- The left half is dedicated to a Sample List View.
- The right half can switch between the **Keymapping View** and the **Sample Waveform View**.

### 4.5.2 Sample List View

In **Edit Mode**, the Sample List View gives you an overview of the samples currently used in the selected Sample Map, as well as options to edit the Sample Map. The Sample List itself displays basic information for all of the samples in the Sample Map: Name, Root note, Low note (L), High note (H), Low velocity (LVel), High velocity (HVel), Embed status, and Location.

Name	Root	L	н	LVel	HVel	Embed	Location
FC27_Fx.wav	26	26	26	0	127	$\checkmark$	[D:\Sample
tomi	27	27	27	0	127	$\checkmark$	[D:\REAKT
tablets	28	28	28	0	127	$\checkmark$	[C:\REMM
SA40_Drm_ride	29	29	29	0	127	$\checkmark$	[D:\Sample
EC27	30	30	30	0	127	$\checkmark$	[C:\REMME
METALs	31	31	31	0	127	$\checkmark$	[C:\REMM
EA24Fx	32	32	32	0	127	$\checkmark$	[C:\REMM
1EX00050	33	33	63	0	127	$\checkmark$	[C:\REMM
Add Rep	lace	Save	As				Remove

Sample List View (Edit Mode)

In Play Mode, only the Name and Location columns are visible in the Sample List View.

Resynth	<b>•</b>						
Name	Location						
1EX00050	[Ensemble]						
EA24Fx	[Ensemble]						
EC27	[Ensemble]						
FC27_Fx.wav	[Ensemble]						
METALs	[Ensemble]						
SA40_Drm_ride	[Ensemble]						
tablets	[Ensemble]						
tomi	[Ensemble]						
Add Replace Save As Remove							

Sample List View (Play Mode)

Above the Sample List is a drop-down menu (by default labeled Sample) that allows you to navigate between the different sample modules available in the currently loaded ensemble.

► To **open the relevant Sample Map** in the Sample Map editor, select an entry from the dropdown menu.



The drop-down menu containing sample modules

The *Show Sample Module in Structure* button to the right of the Sample menu provides immediate access to the sample module in the Structure:

► To **display the currently selected sample module in the structure** of the ensemble, click the *Show Sample Module in Structure* button.

Resynth	-	Ę					
Name	Root	2	н	LVel	HVel	Embed	Location
FC27_Fx.wav	26	26	26	0	127	$\checkmark$	[D:\Sample:
tomi	27	27	27	0	127	$\checkmark$	[D:\REAKT(

The Show Sampler Module in Structure button



The Show Sampler Module in Structure button is only available in Edit Mode.

## **Sample Embed Status**

The Embed status of a sample can be changed by clicking on the sample's check box.

Name	Root	L	н	LVel	HVel	Embed	Location
8MX00021	71	71	71	0	127	$\checkmark$	[C:\REMMER\
AZ-CLAP	76	76	76	0	127	$\checkmark$	[C:\REMMER\
BAUCH2	75	75	75	0	127	R	[C:\REMMER\
Buegelterfal	64	64	64	0	127	⊡	[C:\REMMER\

The Sample Embed Status

• If the box is checked, the sample will be embedded in the ensemble file when it is saved.

• If the box **is not checked**, the sample will be referenced from its location on your computer's hard drive.



If a number of samples are selected when you check or uncheck the Embed checkbox, all samples will be affected in the same manner.

Un-checking the Embed checkbox of a sample that is currently embedded with the ensemble will open a Save Audio File dialog box to ensure the sample exists on your hard drive and can be located by REAKTOR. When this dialog box opens:

- 1. Navigate to a location to which you wish to save the current sample. Enter a name for the file in the File name field. Note that if a file path exists, REAKTOR will just save to that location without asking.
- 2. Click Save to save the sample.

If you click Cancel , the process will abort and leave the sample embedded in the ensemble.

#### To un-embed multiple samples:

- 1. Select the samples you want to un-embed in the Sample List.
- 2. Uncheck the Embed checkbox of one of samples.
- 3. A Save Audio File dialog box will open to ensure the sample exists on your hard drive and can be located by REAKTOR.
- 4. When this dialog box opens, navigate to a location to which you wish to save the samples. Enter a name for the file in the File name field. Note that if a file path exists, REAKTOR will just save to that location without asking.
- 5. Click Save to save the samples.

When saving multiple samples, the Save Audio File dialog will only ask for the first selected sample's file name, and will save all other samples to the same file path location under their current names.

## Sample Map Editing

In the Sample List View you can edit the Sample Map in various ways. The most important and commonly used options are accessible as buttons below the Sample List.

CONG_SHAK	67	67	67	0	127	$\checkmark$	[C:\REMMER\
CYMBAL	82	82	82	0	127	$\checkmark$	[C:\REMMER\ 💝
•							► E
Add Rep	Remove						

Sample List Edit Buttons

- Add: Opens a window to add a sample from your hard drive to the currently selected Sample Map.
- Replace: Similar to Add, but will load the new sample in place of a sample that was selected in the Sample List.
- Save As: Opens a window allowing you to export a selected sample as a .wav or .aiff file.
- Remove: Deletes the currently selected sample(s).



Using the Remove command to delete embedded samples will remove the samples (i.e. audio files) from the hard disk.

As well as the above, additional edits are also available by right-clicking (Mac OS X: [CTRL] + click) on the list itself.

Resynth 👻 🛋								
Name		Root	L	н	LVel	HVel	Embed	Location
FC27_F	way	26	26	26	0	127	$\checkmark$	[D:\Sample
tomi	উAdd				0	127	$\checkmark$	[D:\REAKTO
tablets	Replac	е			0	127	$\checkmark$	[C:\REMME
SA40_D	Save A	s		F	0	127	$\checkmark$	[D:\Sample:
EC27	Remov	/e			0	127	$\checkmark$	[C:\REMME
METALs	Note A	ctions			0	127	$\checkmark$	[C:\REMME
EA24Fx	Clear L	ocation	ı		0	127	$\checkmark$	[C:\REMME
1EX0005	Reload				0	127	$\checkmark$	[C:\REMME
4	Show i	in Folde	er					Þ
	Extern	al Edit		1				
Add	Sample	e Map		۲.				Remove
				-				

Sample List Edit Menu

• *Note Actions*: Quick mapping actions for selected samples.

- Set Root Note to Low Note: Sets the Root value of the selected samples to their Low value.
- *Remap to Single Notes*: Especially when working with Sample Maps where one drum sample is assigned to each note, it can be time-saving to have REAKTOR automatically assign one note to each sample. If you want to take advantage of this feature, load all the desired samples into the Sample Map and choose the *Remap to Single Notes* menu entry.
- *Clear Location*: For selected embedded samples, removes the sample location information.
- *Reload*: If the sample is not embedded in the ensemble, this command will update the sample in REAKTOR if it was edited externally since the initial loading.
- Show in Folder: Opens a system folder at the location of the currently selected sample.
- *External Edit*: Opens the currently selected sample in a sample editing program (if specified in the Preferences).
- *Sample Map*: provides access to a number of additional import and export options via a sub-menu:
  - *Import (merge)*: adds the content of the imported Sample Map to the already existing one.
  - *Import (replace)*: replaces the current Sample Map with the imported one.
  - *Export including Audio Data*: saves a Sample Map including samples (i.e. audio files.) Audio data is included, which means the Sample Map file may get rather big in file size. Use this option if you intend to share the resulting Sample Map file with other users.
  - *Export with References Only*: saves a Sample Map with file references. Audio data is excluded, which means the Sample Map file will be very small in file size. The *Export with References Only* option is only available when none of the samples are embedded.

## Improved Dragging and Dropping of Samples and Sample Maps

In REAKTOR 5.8, you can drag and drop files from the REAKTOR browser to the Sample Map list is as follows:

- Samples: *adds* the sample to the list
- Sample Maps: replaces the entire list

**Holding down the [SHIFT] key on your computer keyboard** before dropping the sample or Sample Map adds these options:

- Samples: *replaces* the sample at the drop location.
- Sample Maps: *merges* the new sample map with the current list.

## 4.5.3 Keymapping View

The Keymapping View can be used to arrange the samples on a virtual keyboard, allowing you to quickly define the root note, note ranges and velocity ranges of the currently loaded samples.

The Keymapping View is accessed by clicking on the Map button above the right half of the Sample Map Editor.



The Keymapping View

The main area of the Keymapping View displays a virtual keyboard with the samples arranged as boxes above it. These boxes show the current note range and velocity range of the samples. The horizontal axis of this area represents MIDI notes, and the vertical axis represents MIDI Velocity.

The following edits are available via this area:

- To **select a sample**, clicking on a box (the selection will be reflected in the List View).
- To **select multiple samples**, click on an empty space and drag a lasso selection around the samples you wish to select.
- To change the note range and root note for the sample, move the box. The root note is highlighted in blue on the virtual keyboard.
- To **change the root note of the sample**, click and drag the highlighted note on the virtual keyboard.
- To change the velocity/note range of the sample, resize the box.

The current view range can be adjusted by using the scroll bars and zoom buttons to the bottom and right of the Keymapping View.

With a single, or multiple selection of samples, you can use the value fields below this area to enter exact data for the Sample Map:

- Root: Sets the root note of the sample. Commonly, this is the natural note of the sample. If this note is played, no transposition will take place.
- Low: The lowest MIDI note that triggers the sample.
- High: The highest MIDI note that can trigger the sample. Any note between the Low and the High will also trigger the sample.
- LVel: The lowest velocity that will trigger the sample. A MIDI velocity between this value and the HVel setting will trigger the sample.
- HVel: The highest velocity that will trigger the sample.

The following **additional functions** are available in this area:

- Tune: Sets the tuning of the sample that is applied before any further transposition takes place.
- Gain: sets a gain factor applied to the sample.
- Pan: sets a stereo panorama setting for the sample.



The Gain and Pan controls are not available for all sampler modules.

## The Keymapping View Context Menu

► To access a context menu that provides access to additional functions in the Keymapping View, right-click (Mac OS X: [CTRL] + click) a selected note.

The context menu provides access to these options:

- *Remove*: Removes the selected sample(s).
- Set Root Note to Low Note: Sets the Root value of the selected samples to their Low value.
- *Remap to Single Notes*: Especially when working with Sample Maps where one drum sample is assigned to each note, it can be time-saving to have REAKTOR automatically assign one note to each sample. If you want to take advantage of this feature, load all the desired samples into the Sample Map and choose the *Remap to Single Notes* menu entry.



The Keymapping View context menu

## 4.5.4 Waveform View

The Waveform View can be used to view the waveform of the currently selected sample as well as offering a selection of controls to alter the sample's settings.

The Waveform View is accessed by clicking on the Waveform button above the right half of the Sample Map Editor.

Map Waveform					Externa	l Edit	¢ -
BAUCH2.wav				4410	00 Hz	1.21 s	
0.0ms 10.192.5ms	384.9ms	0.6s	1	0.8s	1.0s	1.2	ŝ ^
kiliti.							
	*******						11
a a a a a a a a a a a a a a a a a a a	taaaaaa	~~~~~	~~~~~				
- <b>1111</b> + 1 + 2 · ·							
11.11							+
Reverse Start							
Loop 0	0						

The Waveform View

The main area of the Waveform View is of the waveform itself. Below the waveform is a selection of controls:

- Reverse: Check this box to play the sample backwards from the end of the sample, or the end of the loop.
- Loop: toggles on or off the looping of the sample, or a portion of the sample.



Loop controls are not available for all sampler modules.

- Start: sets the start point of the loop (in samples)
- End: sets the end point of the loop (in samples)
- Alternate: checking this box will make the loop play forwards, then backwards alternately.
- Release: check this box to continue looping after a note off message.
- Phase Align: applies signal analysis to align grains (only available in granular modules)

If looping is active, it is possible to **adjust the start and end times** by clicking and dragging on certain parts of the Waveform View:

- The flag at the start of the waveform will move the loop start time.
- The flag at the end of the waveform will move the loop end time.

- **Clicking and dragging** anywhere between these points will move both the start and end times equally.

The looped area will be highlighted white, and the non-looped areas will be colored blue.

# 4.6 Updates to Mouse Controlled Elements

Mouse controlled elements are any panel elements that use the click-and-drag function to change a value. These include:

- Knobs
- Faders (both horizontal and vertical)
- XY
- Mouse Areas
- Multi-Pictures

A number of changes have been made to the behavior of these elements in REAKTOR 5.8.

## 4.6.1 Fine-tuning

Fine-tuning is now available for mouse controlled elements. With fine-tuning activated, the control will move more slowly, and with finer resolution, depending on the properties of the element.

► To activate fine-tuning, hold the [SHIFT] key on your computer keyboard as you click and drag a control.

## Fine-tuning Factor

Q	Ď	I+†	V		
Filter Cutoff		Fader 🔳			
FUNCTION	INFO	VIEW	CONNECT		
RANGE					
Max		Stepsize			
1		0			
Min		Mouse Resolution			
0		360			
Default		Fine-tuning Factor			
0.5		10			

Fine-tuning is located to the bottom right.

Located in the Function tab of the properties window, the Fine-tuning Factor can be any positive integer value. This value will be multiplied to the Mouse Resolution value when the [SHIFT] key is held.

## Fine-tuning in Ensembles Saved before REAKTOR 5.8

Because the updates that enable fine-tuning may alter the behavior and sound of legacy ensembles, controls that were created in a REAKTOR version before 5.8 run in a special legacy mode with fine-tuning disabled.

► To enable fine-tuning for such a control, click on the Fine-tuning Factor field that displays the text <not enabled>. This is an undo-able action but cannot be reverted once the ensemble has been saved.

RANGE	
Max	Stepsize
1	0.000277778
Min	Mouse Resolution
0	360
Default	Fine-tuning Factor
0.5	<not enabled=""></not>

Apart from setting the fine-tuning factor to 10 and the step size to zero, enabling fine-tuning for a legacy control may change the interpretation of its value stored in any snapshot, preset or host project by the order of the step size.

## 4.6.2 Other Updates

A variety of other updates have been applied to the controls. These updates will only be applied to controls created in REAKTOR version 5.8 or later, or to any control with fine-tuning activated. Otherwise, they will function as before, in order to preserve compatibility.

### **Stepsize Defaults to Zero**

A setting of zero for this property will mean that the output of the control is calculated as a 32bit floating point value between 0 and 1, which is then scaled to the Min and Max settings.

#### Num Steps removed from Properties

The Num Steps property has been removed, as it can be calculated from the Min, Max and Stepsize properties. This also means that Stepsize property is given priority over the number of steps when making changes to the Min and Max properties.

### Mouse Resolution Ignored for anything but the Mouse and Keyboard

In REAKTOR versions prior to 5.8, the Mouse Resolution property would affect external controls, including MIDI, OSC, host automation, as well as internal connections (IC send & receive). Now these values are only quantized by the Stepsize property, resulting in less rounding errors and more predictable behavior.

# 4.7 Bookmark Behavior for Screensets

In REAKTOR 5.7 Screensets were introduced. Originally, the selected Screensets would be automatically updated as any updates to the current view were made. In REAKTOR 5.8, Screensets can be changed to behave more like Bookmarks, and only be updated when they are created, not when you navigate around the structure.

### **Activating Bookmark Behavior**

To activate bookmark behavior for Screensets:

- 1. Enter the View menu
- 2. Navigate to *Screensets*

3. Select and click on Bookmark-like Behavior to check this option

It is possible to switch between modes using this option, depending how you wish to work.

# 4.8 Updated Screenset Options

The following options are now available when right-clicking on a Screenset.



Expanded Screenset Options

- *Rename*: names of Screensets default to the name of the location of the Screenset, however a new name can be specified by selecting this option.
- *Replace*: over-writes the selected Screenset with the current view. (Only available when Bookmark-like Behavior is active)
- *Move Up*: relocates the selected Screenset to one position up (moving Screenset 4 to position 3, for example). This will affect both the order of icons and the keyboard shortcuts.
- *Move Down*: relocates the selected Screenset one position down.
- Delete: removes the selected Screenset.

### **Updated Keyboard Shortcuts**

The keyboard shortcuts for Screensets have been updated to replace the Panelset shortcuts for faster navigation through the structure of an ensemble. Please refer to section *†*8, Keyboard Shortcut Overview of this manual for the most up to date list of keyboard shortcuts.

# 4.9 Updated Sample Rate Settings

The sample rate menu, accessed by clicking on the displayed sample rate display to the right of REAKTOR's header, has been updated with more options.



Sample Rate Menu

The sample rate menu contains three main categories, with a variety of options:

- *Host/System*: This option links REAKTOR's sample rate to the host or system sample rate. This is the default setting and probably the best to use for most cases.
- *Fixed*: Picking any of these options will fix the sample rate for the ensemble. This setting will be saved with the ensemble and recalled whenever it is loaded. The options available are multiples of the host/system setting and allow for internal over-sampling.
- *Factor*: Select from any of these options to increase or decrease the internal sample rate as a factor of the system/host sample rate. This setting is a REAKTOR preference and will be recalled when you next open REAKTOR (unless you open an ensemble with a fixed sample rate).

# 5 What's New in REAKTOR 5.7?

Welcome to REAKTOR! This manual addendum provides information about the new features in version 5.7 of REAKTOR. Here is a brief overview of the most important changes and additions:

- Improved loading times (†5.1, Compiled Core Cell Code Cache)
- ↑5.2, Explicit Play and Edit Modes
- <sup>†5.3</sup>, Screensets
- <sup>†</sup>5.4, Universal Wire Debugging Mode
- *†*5.5, Layout and Transport Changes

# 5.1 Compiled Core Cell Code Cache

When opening an Ensemble with large Core Cell structures in REAKTOR 5.7, a cache file of the compiled Core Cell code is saved on your hard drive. When you next load the Ensemble, REAKTOR will access this cache file, allowing it to skip this compiling stage of the loading process to significantly decrease loading times.

## Important Details of the Compiled Core Cell Code Cache Feature

- The Compiled Core Cell Code is only used when REAKTOR is in Play Mode (see ↑5.2.1, Play Mode).
- Switching to Edit Mode (see ↑5.2.2, Edit Mode) when using Ensembles with large Core Cell structures causes a re-load of the Core Cells, which can cause REAKTOR to pause momentarily.
- The loading time optimization only works for Ensembles saved with REAKTOR 5.7 or later.

## **Default Cache Location**

The default location of the Compiled Core Cell Code Cache is:

• On Windows: .../<user>/AppData/Local/Native Instruments/Reaktor5/Cache/

• On Mac OSX: .../<user>/Library/Application Support/Native Instruments/Reaktor5/Cache/

## **Changing the Compiled Core Cell Code Cache Location**

To change the Compiled Core Cell Code Cache location:

- 1. Open the Preferences window by clicking on *Preferences...* in the File menu or by pressing [Ctrl] + [,] on PC or [Cmd] + [,] on Mac.
- 2. Navigate to the Directories tab. At the bottom of the Directories tab you will see an area labeled Compiled Core Cell Code Cache.



- 3. To change the Cache location, either click the browser button on the left to locate the target directory on your system, or type in the location manually.
- 4. Close the window.
- 5. If your operating system prompts you, allow REAKTOR to make changes to your hard drive.

## Purging the Compiled Core Cell Code Cache

To delete all unused or corrupt files from the Cache directory, click on the Purge button in the Compiled Core Cell Code Cache preferences. These files will be deleted:

- Any Compiled Core Cell Code file for which the parent Ensemble can no longer be found
- Any corrupt Compiled Core Cell Code files

You can remove all of the files in the Cache manually, but REAKTOR will re-create the Compiled Core Cell Code files the next time you load Ensembles containing large Core Cell structures in Play mode.

# 5.2 Explicit Play and Edit Modes

New in REAKTOR 5.7 are dedicated Play and Edit modes that optimize REAKTOR for playing and for editing Ensembles.

## 5.2.1 Play Mode

REAKTOR 5.7 introduces a new Play Mode, which optimizes REAKTOR for the case of using, rather than editing Ensembles. The main benefits of Play Mode are:

- Streamlined interface to maximize the Ensemble Panel space: In Play mode, all of the editing controls are hidden and disabled, presenting a more streamlined workspace for those who do not need all of the editing capabilities of REAKTOR, but want to use instruments and effects built in REAKTOR.
- **Optimized loading times for Ensembles:** Play Mode is required to be active in order for RE-AKTOR to use the new Compiled Core Cell Code Cache, and so can decrease loading times of larger Ensembles significantly.
- Easier use of REAKTOR as a plug-in: Play Mode also makes working with REAKTOR as a plug-in easier by disabling any control options that are not saved in a Host Chunk that is to say, any options that require you to save the Ensemble file when you are using RE-AKTOR as a plug-in. This means you no longer need to worry about the auto-save functions and host recall for your projects.

## Features and Options Unavailable in Play Mode

The following controls and options are disabled when using Play Mode:

- Entering the Ensemble structure
- Editing the Panel
- Storing and recalling Panelsets
- Viewing or editing the properties of any element
- Changing the Control Rate or Sample Rate
- Snapshot and Bank editing (though loading snapshots is still possible, saving is only possible by saving with the Host Chunk or by saving a single preset)
- Sample Map editing
- MIDI Learn

## 5.2.2 Edit Mode





REAKTOR 5.7 now has an explicit Edit Mode that is similar to the classic workspace of previous REAKTOR versions. In this mode, all of the controls related to changing the structure or options of an Ensemble are present and visible.

► To activate Edit Mode, click on the button with the Structure icon to the left of the Snapshot Selection menu in the Header or use the keyboard shortcut [F1].

Explicit Play and Edit Modes



A comparison of Sinebeats2 in Edit Mode on the left, and in Play Mode on the right

The Edit Mode setting is persistent between sessions when using REAKTOR in stand-alone mode. If you use REAKTOR mainly to build or edit your own Ensembles, it is possible to activate Edit Mode and leave REAKTOR in this state for each time you return to it.



Creating a new Ensemble will automatically activate Edit Mode.

# 5.3 Screensets

Screensets are a new tool to help you navigate your Ensembles. They are located in the sidebar, below the Debug and MIDI Learn buttons.



The Screensets are located in the sidebar

Screensets are like Bookmarks from previous REAKTOR versions, but include two major improvements: the use of keyboard shortcuts, and saving the state of your workspace — your current workspace set up is automatically saved in your currently selected Screenset.

The icon for a specific Screenset depends on its contents (Pane, Structure, or both) and the orientation of the screen split (if used).

Any Ensembles created or saved in a REAKTOR version earlier than 5.7 will have their Bookmarks imported as Screensets. A new Ensemble will automatically have two Screensets: The Panel, and the Ensemble structure.

## 5.3.1 Creating Screensets

To create a new Screenset, either

- click the + button below the Screensets, or
- ▶ pressing [Ctrl] + [T] ([Cmd] + [T] on Mac) on your computer keyboard.

## 5.3.2 Deleting Screensets

To delete a Screenset, either

▶ right-click the Screenset icon and select *Delete Screenset*, or



▶ close all of the Panes in the workspace.



[Ctrl] + [F4] ([Cmd] + [W] on Mac) closes your current Pane. If this closes the Screenset, then it is removed from the list.

## 5.3.3 Navigating Screensets

The following keyboard shortcuts have been added to make navigation of your Ensembles even quicker and easier.

Action	Mac OS X	Windows
Append Screenset	[Cmd] + [T]	[Ctrl] + [T]
Recall Screenset 18	[Ctrl] + [Cmd] + [18]	[Ctrl] + [Alt] + [18]

Universal Wire Debugging Mode

Action	Mac OS X	Windows
Next Screenset	[Ctrl] + [Tab]	[Ctrl] + [Tab]
Previous Screenset	[Ctrl] + [Shift] + [Tab]	[Ctrl] + [Shift] + [Tab]
Close Pane / Screenset	[Cmd] + [W]	[Ctrl] + [F4]

► To select a specific Screenset, click on the corresponding icon.

# 5.4 Universal Wire Debugging Mode

In REAKTOR 5.7 there is no longer a distinction between debugging wire values in Primary or Core. Instead, there is now one universal debugging mode that remains persistent when navigating between Core and Primary structures. As an added benefit, viewing the values of cables in Primary is now no longer linked to the Info Hints setting.

► To activate Wire Debugging Mode, either click on the bug icon below the MIDI Learn button in the Sidebar, or press [Ctrl] + [B] ([Cmd] + [B] on Mac).



Enable Wire Debugging

► To view a wire's value, hover the mouse cursor over the wire.

The format in which the values are presented have been updated slightly to highlight the difference between wire values and Info Hints.



A comparison between Info Hints (left) and a wire value (right)

# 5.5 Layout and Transport Changes

The main changes to the layout of REAKTOR 5.7 are:
- Edit Mode button in Header.
- Changes to the Sidebar to include Screensets.
- Audio Recorder and Player have moved into the Header area.

#### Updated transport controls.



The Updated Header, including the Recorder Bar

The Transport controls have been updated to work in a more logical fashion:

- The Play button starts and pauses playback.
- The Restart button sets the Song Position to zero, but will not alter the playback state.

# 6 What's New in REAKTOR 5.6.2?

The following are a list of changes introduced before 5.7, but that are still applicable to the addendum:

- 64-bit support for Windows and OS X
- New Module Reference manual
- Simplified handling of Snapshots
- Easily save the state of an existing Ensemble as a Preset file
- Quickly navigate Structures using the breadcrumb navigation feature
- Scroll the Structure with [Alt]+Drag
- Show the previous Structure with [Alt]+[B]
- Show the contents of a Macro in the other Split Pane with [Alt] + double-click on the Macro
- Add Objects to the Structure using the Searchbox (just press [Enter] in Structure View)
- Delete Objects and Wires using [Backspace] or [Delete]
- Duplicate Objects with [Ctrl] + Drag ([Alt] + Drag on OS X)
- Drag copies of Objects to the other Split Pane with [Ctrl] + Drag ([Cmd] + Drag in OS X)
- Navigate to the parent folder in the Browser's folder tree with Left Arrow
- The Recorder Bar now shows the recorded time when recording
- The XY Module now features the "transparency" and "hide frame" properties
- Improved loading time for Ensembles with many Send and Receive Modules
- Added "Abort" function to the File Not Found dialog upon project recall
- Changed keyboard shortcuts

Bug fixes and latest changes of this update are documented in the README.TXT file which was copied to your hard disk along with this document. For all other questions regarding RE-AKTOR, please refer to the Getting Started Manual, Application Reference, and Module Reference. This addendum assumes that you have a basic understanding of what is explained there.

# 6.1 Improved Structure Navigation

REAKTOR version 5.6.2 now comes with a number of usability enhancements that make navigating Structures a breeze.

# 6.1.1 Breadcrumb Navigation

The breadcrumb navigation feature lets you directly access different hierarchy levels of the Structure. This feature is activated when Edit mode is turned on. The breadcrumb navigation basically displays a view of the hierarchical levels above the currently shown Ensemble Structure. To jump to a higher level, just click its entry in the path display. REAKTOR also displays the last lower-level Structure you visited, so that you can quickly return to that Structre's level with a mouse click. For a walkthrough of the breadcrumb feature, follow these instructions:

1. First, open an existing Ensemble with at least a couple of Structure hierarchy levels. Here we use Padecho.ens, found in the Factory Content section of the Browser. More precisely, it is located under *Ensembles > Tutorial Ensembles > Padecho.ens*.

2. Make sure you are in the Ensemble's Panel View, as shown in the figure below.



3. Now turn on the Ensemble's Edit mode by using the keyboard shortcut [F1] or by pressing the Edit button, shown in the figure below.



4. Now you should see the breadcrumb navigation, as shown in the figure below. It displays a hierarchical view of the Ensemble Structure, including the Panel. The current location is highlighted. In our case we are in Panel View, so the Panel entry in the path interface is highlighted (see figure below). To navigate one level down in the Structure using the breadcrumb navigation, left-click the next path element.



5. As expected, you have navigated one level down in the Structure. Accordingly, the corresponding path entry is highlighted. This is shown in the figure below.



6. Now let's split the Structure by left-clicking the Horizontal Split button, shown in the figure below. Alternatively you can use the keyboard shortcut [F2].



7. You should see the Split View with two Structures, as shown in the figure below. Note that each Split Pane has its own breadcrumb navigation interface. In the top Pane, navigate one level deeper into the Structure. The breadcrumb navigation shows the lowest level in the Structure navigated to. In the case of the figure below, the Master Instrument was the lowest Structure level visited. The idea of the breadcrumb navigation is to easily navigate through complex Structures. If the breadcrumb navigation does not display all of the Structure's levels, just navigate as usual by double-clicking the desired Objects in the

Structure. This will add the levels you have visited to the breadcrumb navigation bar. Both Split Views have their own breadcrumb navigation interface:

Panel ►	Padecho	Master					
		Pad	Out C	InR Echo stereo		– Out Out	1
						_	
Panel →	Padecho						
		<b>II III</b> Pad	Out	InL InR Echo stereo	L P R P	– Out – Out	1 📕 2 📕

→ The figure below shows the result of the last navigation operation. Each of the Split Panes can be navigated independently with their own breadcrumb navigation interfaces.



To quickly toggle between the Panel View and the current Structure View:

▶ Press the Edit button (or [F1] key on your computer keyboard), shown in the figure below.



Use the Edit button to toggle the Edit mode on and off.

Alternatively, you can use the Close button, shown in the figure below, to close a Split Pane. If only one Structure Pane is shown, pressing the Close button directly navigates you to the Panel View. Pressing the Close button in Panel View turns the Edit mode off.



The Close button at the very right of the breadcrumb navigation interface.

If you have reached Panel View by repeatedly pressing the Close button as described above and you then press the Edit button, you will return to the Split Pane setup displayed before you first pressed the Close button. That is, even if you first closed a Structure Split Pane, you will be returned to the Split View.

# 6.1.2 Other Structure Navigation Improvements

#### **Opening a Macro in the Other Split Pane**

► To show the contents of a Macro in the other Split Pane, double-click the Macro while holding down the [Alt] key. This is shown in the sequence of two figures below. The red outline indicates that the displayed Structure is indeed the contents of the Macro.



This also works for Instruments, Core Cells and Core Macros.



Open the contents of a Macro in the other Split Pane by double-clicking it while holding down the [Alt] key.



The breadcrumb navigation interface indicates that the content of the Structure is indeed that of the [Alt] + double-clicked Macro.



You can also perform the same action by right-clicking the Macro and selecting the *Structure in other Pane* menu entry.

#### Scrolling the Structure with the Mouse

► You can now scroll the Structure by clicking and dragging the Structure background while holding down the [Alt] key. During this operation the mouse cursor should change shape. This is shown for the case of Windows in the figure below.



Scroll the Structure by clicking and dragging while holding down the [Alt] key.

# 6.2 Improved Object Manipulation

In addition to the navigation improvements discussed in the previous chapter, building in RE-AKTOR has now been made faster and more efficient in a number of ways. For example, you can use the Searchbox to directly type in the name of the Object you wish to load without having to search around for the right menu entry. Also, new keyboard shortcuts have been implemented so that you can quickly duplicate Objects, even between different Split Panes.

# 6.2.1 Adding Objects with the Searchbox

To add Objects to the Structure using the Searchbox, follow the instructions below:

1. With the keyboard focus in the Structure View, press the [Enter]/[Return] key or use the combination [Ctrl]+[F] in Windows ([Cmd]+[F] in Mac OS X). This opens up the Searchbox, as shown in the first figure below.



Alternatively, you can right-click the Structure background and choose the *Insert Module* ... menu entry. This is shown in the second figure below.



2. Once the Searchbox has been opened, start typing the name of the Object you wish to place into the Structure. As shown in the figure below, typing "Sine Bank" narrows down the menu of Objects down to the Sine Bank Oscillator Module and the Sine Bank Macro.



- 3. Now choose the Object you wish to load by navigating to the corresponding menu entry using the [Up] and [Down] Arrow keys or simply by clicking on the menu entry.
- 4. After having added some Objects with the Searchbox notice how the last eight Objects you added automatically appear in the Searchbox menu before you have typed anything in the edit field. This is shown in the figure below.



→ The last eight Objects that were added using the Searchbox appear in the menu right after opening the Searchbox.

If you wish to close the Searchbox without adding anything to the Structure, just press the x icon at the right of the Searchbox (or the [ESC] key on your computer keyboard).

# 6.2.2 Other Structure Workflow Improvements

Additionally to the Searchbox, improvements have been made in the way Objects are removed, copied, and duplicated in Structure View.

#### **Deleting Wires and Objects Using Backspace or Delete**

► To delete a Wire or Object from the Structure, just select the desired element and press the [Backspace] or [Delete] key. A selected Wire is shown in the figure below.



You can now use either the [Backspace] key or [Delete] key to remove Objects and Wires from the Structure.

## **Duplicating Objects with Ctrl-Drag**

➤ You can now quickly duplicate Objects in the Structure by holding down [Ctrl] in Windows ([Alt] in Mac OS X) and then clicking an Object and dragging to an empty part of the Structure. A duplicate of that Object will appear at the site of the Structure where you release the mouse button. This sequence of two steps is shown in the two figures below.



To duplicate an Object, hold down [Ctrl] in Windows ([Alt] in Mac OS X) and click and drag the Object to an empty part of the Structure.



The duplicate Object will appear in the part of the Structure where you release the mouse button.

#### **Copying Objects to the Other Split Pane**

► You can now easily copy Objects from one Structure Split Pane to the other by holding down [Ctrl] in Windows ([Alt] in Mac OS X) and then clicking and Object and dragging to an empty part of the other Split Pane. A duplicate of the selected Object will appear at the site of the other Split Pane Structure where you release the mouse button. This sequence of two steps is shown in the two figures below.



To copy an Object to the other Split Pane Structure, hold down [Ctrl] in Windows ([Alt] in Mac OS X) and click and drag the Object to an empty part of the other Split Pane Structure.



A copy of the Object will appear in the part of the other Split Pane Structure where you released the mouse button.

# 6.3 Miscellaneous Improvements

This chapter covers various improvements, such as new hat propeties in the XY Module, 64 Bit compatibility, quicker Browser navigation and the improved Recorder Bar display.

# 6.3.1 XY Module

The XY Module now features the transparency property and the option to hide the frame in Panel View.

## Panel Element Transparency Setting

- 1. To turn on transparency for the background of the XY Module's Panel Element, first go to the Module's Properties View.
- 2. Then enter the View page.
- 3. Now enter the desired transparency value into the Background Color Transparency edit field, shown in the figure below. '100' corresponds to completely transparent and '0' corresponds to completely opaque.



4. The result of an 80% transparency value is shown in the figure below. If need be, go to the Instrument's Panel View to see the result of your transparency setting.



## **Hiding the Panel Element's Frame**

- 1. To hide or display XY Module's frame in Panel View, first go to the Module's Properties View.
- 2. Then enter the View page.
- 3. To hide the XY Module's frame, disengage the Has Frame checkbox, shown in the figure below. On the other hand, to display the frame, make sure the Has Frame checkbox is engaged.



4. The result of hiding the Panel Element's frame is shown in the figure below. If need be, go to the Instrument's Panel View to see the result of hiding the frame. The XY Module's Panel Element without the frame:



# 6.3.2 64 Bit Support

REAKTOR is now compatible with 64-bit processor architectures. This will enhance your RE-AKTOR experience provided that you are running REAKTOR on a computer that utilizes a 64bit processor. On 64-bit Windows operating systems, you can select where to install the 32-bit and 64-bit plug-in versions of REAKTOR during the REAKTOR installation procedure.

# Mac OS X: Switching between 32-Bit and 64-Bit Mode

In Mac OS X you can switch between running REAKTOR in 32-bit and 64-bit modes:

- 1. To switch between running REAKTOR in 32-bit and 64-bit mode (in Mac OS X), open the Get Info window by pressing [Cmd]+[F] on the Reaktor 5.app in the OS X "finder" application.
- 2. Then use the Open in 32-bit mode checkbox to toggle the 32-bit mode on and off. This is shown in the figure below.

🤭 🔿 🙆 Reaktor 5 Info
Reaktor 5 79.4 MB Modified: Today 4:47 PM
▼ Spotlight Comments:
▼ General:
Kind: Application (Intel) Size: 79.4 MB on disk (79,317,948 bytes) Where: /Applications/Native Instruments/Reaktor 5 Created: Yesterday 6:20 PM Modified: Today 4:47 PM Version: 5.6.1 (R11129), Copyright © 2011 Native Instruments Label: X Open in 32, bit mode
More Info:
▼ Name & Extension:
Reaktor 5.app
✓ Hide extension
♥ Preview:

Sharing & Permissions:

Engage the "Open in 32-bit mode" checkbox to run REAKTOR in 32-Bit mode (in Mac OS X).

# 6.3.3 Browser Navigation

Browser navigation has been improved by letting you navigate to the parent folder in the Browser's folder tree with the left Arrow key. The instructions below demonstrate this feature:

1. Open the Browser and in the folder tree, navigate to a folder which lies within another folder. This is shown in the figure below, where the folder tree has the Tutorial Ensembles folder selected. This folder lies within the Ensembles folder.



2. Now press the left Arrow. If the selected folder is in its "closed" state, this will select the parent folder. In our case this is the Ensembles folder, shown in the figure below.



3. Press the left Arrow key again. In the case of an "open" folder, this closes the folder's branch in the folder tree, as is shown in the figure below. The right Arrow key opens the folder in the folder tree again.



# 6.3.4 Recorder Bar

The Recorder Bar now conveniently displays the length of the time interval recorded. This is shown in the figure below.



The Recorder Bar displays the recorded time of the current recording.

# 6.3.5 Supported Graphics Formats

As from REAKTOR 5.6, Modules capable of loading graphics files support the PNG file format, in addition to TGA and BMP graphics files. Independent of the file format, the loaded graphics files can be used as Picture, Multipicture, Knob, etc.

# 6.4 Snapshots

#### How to Read this Chapter

REAKTOR 5.6.2 features simplified Snapshot handling. Additionally, you can easily save and load the complete state of an existing Ensemble as a handy Preset file. This chapter may be read in two ways, depending on what you already know about the Snapshot tab:

- If you are already familiar with the Snapshot tab of REAKTOR 5.5, and have read the chapter on the Snapshot tab in the Application Reference, you can get a good overview of the differences between the new and old Snapshot behavior by just reading sections ↑6.4.8, Defining Snapshot Behavior for Instruments and ↑6.4.9, Opening and Saving Presets. Use the cross-reference links to directly jump to these sections.
- For those who are not yet familiar with REAKTOR's Snapshot tab, you should read the whole chapter, as it contains a complete guide to using the Snapshot tab, including the new features.

#### What are Snapshots?

Snapshots (also known as patches, programs, or presets) enable you to store and recall an Instrument's sounds. When you create a Snapshot, the current settings of all the Instrument's Panel controls and MIDI controllers are stored in the Snapshot. Among the Panel controls, settings like the knob and fader positions, list box and switch settings, and button states are saved. When you recall a Snapshot, all the Instrument's controls are restored to the settings they were in when the Snapshot was originally created. Each REAKTOR Instrument can store 16 Snapshot Banks containing 128 Snapshots each, for a total of 2048 Snapshots. In this chapter you will learn how to recall and create Snapshots in addition to working with Snapshot Banks and features like "Snapshot Compare" and "Snapshot Randomize". All of these features are accessed from the Snapshot tab (see below).

Q		נ נ	h.	
GoBo	x		-	Linked
#	Banks		Ec	lit 🔻
001	His Bank			
002	Her Bank	c		
le s	napshot M	orphing +	Rando	m
1				I
1: 18	3 - Lofi I	1.00	de	fault
Ran	domize	100	Rnd.	Merge
#	Snapshot			
001	Set the S	cene		
002	Add the (	Groove		
003	Table Te	nnis		
004	Deep Vib	ration		
005	Stop and	Go		
006	Stop and	Go Two		
007	Gop and	Stop		

The Snapshot tab lets you do all the possible Snapshot operations in REAKTOR.

# 6.4.1 Recalling Snapshots

There are five different methods you can use to recall an Instrument's Snapshots:

The first way to recall a Snapshot is by using your mouse to select the desired Snapshot from the Snapshot drop-down menu in the header, shown in the figure below. When using REAKTOR as a plug-in, it is this Ensemble Snapshot List which is forwarded to the host application. The Snapshot List always shows the Snapshots of the Ensemble or Instrument set as the Snapshot Master (see subsection ↑6.4.8, Defining Snapshot Behavior for Instruments). The Snapshot drop-down menu looks like this:

#### 1 - Baltik State

• You can also use your mouse to select Snapshots from the Snapshots drop-down menu in the Instrument Header (shown in the figure below). With the Instrument header selected, you can use the Up and Down arrow keys on your computer keyboard to select previous and next Snapshots, respectively. The Snapshot drop-down menu in the instrument header:



٥

• Another option is to go to the Snapshots tab. In the Snapshot tab you first need to select the desired Instrument (or Ensemble) for which the Snapshot recall is to take place. This is done using the Select Instrument drop-down menu shown in the figure below. Then click on the Snapshot you wish to recall in the Snapshot List.



- Additionally, you can select Snapshots by sending MIDI Program Change messages from a MIDI keyboard (or some other MIDI device). For this to work, the Recall by MIDI checkbox in the Function page (see subsection ↑6.4.8, Defining Snapshot Behavior for Instruments) of the corresponding Instrument's Properties should be engaged. The MIDI Program Change message selects a Snapshot by its number (an integer in the range [0 ... 127]). A Program Change value of "0" selects the first Snapshot, a Program Change value of "1" selects the second Snapshot, and so on. The Recall by MIDI checkbox:
- Last, if you are a REAKTOR builder, you can use the Snapshot Module to recall, store, randomize, and morph Snapshots. Please read the entry of the Snapshot Module in the Module reference for more information on this Module.

#### **Parent and Child Instruments**

Any Instrument that contains another Instrument is called a "parent" Instrument. For example, an Ensemble (top-level Instrument) that contains another Instrument is a "parent" Instrument. A "child" Instrument is an Instrument that is contained within another ("parent") Instrument.

Recalling a "parent" Instrument's Snapshot recalls the Snapshots of "child" Instruments as well, but only if the Snap Isolate checkbox in the respective Instrument's Function page is disengaged (see section  $\uparrow$ 6.4.8, Defining Snapshot Behavior for Instruments for more information on this).

Note that recalling a "parent" Instrument Snapshot not only recalls the "child" Instrument's Snapshot that was loaded at the time of storing the "parent" Snapshot, but also sets the "child" Instrument's controls to the state in which the "parent" Snapshot was stored.

## Selecting the Instrument for the Snapshot List

If you have several Instruments in your Ensemble, there will be a Snapshot List for each of these Instruments in the Snapshot tab. This will be the case even if some of these Instruments have no Snapshots at all; that Snapshot List will then be empty. The Snapshot tab can only display one Snapshot List at a time. How do you choose the Instrument for which the corresponding Snapshot List should be displayed? There are two ways:

- You can select the Instrument for which the Snapshots are displayed in the Snapshot List from the Select Instrument drop-down menu.
- Another option is to activate the Linked button. If this button is activated, the Snapshot List is linked to the Panel View. This means that if you select an Instrument in Panel View, its Snapshot List is automatically displayed in the Snapshot tab. If the Linked button is not active, you must use the Select Instrument drop-down menu explained above to manually choose which Instrument's Snapshots are displayed in the Snapshot List.

Linked

► To select the Ensemble Snapshot List with the Linked button activated, click an empty area of the Panel View where there is no Instrument Panel.

#### Making a Control Immune to Snapshot Recall

When you select a Snapshot, the Panel controls and MIDI controllers jump to their positions as stored in the Snapshot. In some cases you might not want this to happen. For example, you might create a sequencer with a BPM (tempo) knob whose settings you want to be independent of the Snapshot. To prevent a Panel control or MIDI controller from jumping to the position designated by the Snapshot, follow these instructions:

- 1. Double-click on the desired control like a knob, fader, list, or button.
- This should have opened up the control's Properties View. Now click on the Function button:

## **Control IDs**

Every REAKTOR Panel control has a unique ID number, as displayed in the ID for Files edit field in the control's Function page. This ID number is called the Control ID, and it is shown in the corresponding Edit field (see below).

SNAPSHOTS	
ld for Files	
10653	Snap Isolate
	Mrph/Rnd Isol.

The ID for Files edit field holds the value by which a Snapshot identifies the Panel control.

REAKTOR lets you change these Control IDs. Before you do so, you have to be aware of a few dangers that are tied to this. Snapshots assign specific (control) values to specific Control IDs. For example, Snapshot 1 might assign the value "0.5" to a knob with the Control ID "112" and the value "0.75" to a fader with the Control ID "222", and so on. If you change the knob and fader Control IDs, it will change the values that Snapshot 1 assigns to these controls. Thus you can break Snapshots which you have worked on so arduously.

Do not change the Control ID Numbers unless you really have to. Be aware that changing Control ID Numbers breaks the Snapshots which were used for these controls.

# 6.4.2 Adding and Removing Snapshots

The basic operations that you can do with the Snapshot List are to add, overwrite, and remove Snapshots. This section describes which buttons you need to press for the different Snapshot List operations. Before pressing these buttons, though, you need to make sure that you are working with the Snapshot List of the intended Instrument. You can see which Instrument is selected with the Select Instrument drop-down menu. Also, you need to click the Append, Store, and Insert buttons *twice* for these operations to be finalized. The first click lights up the button and places a blinking cursor in the appended, stored, or inserted Snapshot slot, giving you the opportunity to type a name for it. The second click dims the button and saves the appended, overwritten, or inserted Snapshot.

Ensemble	Linked
Ensemble BeatSlicer Compressor	Edit 🔻
·	
	,

The Select Instrument drop-down menu

Remember to click *twice*! If you forget the second click, you might end up doing something very different from what you intended.

#### **Appending Snapshots**

If you want save the current Instrument settings as a new Snapshot to the first empty slot in the corresponding Snapshot List, then use the Append button in the Snapshot List Operations area. If the current Snapshot Bank is full, pressing the Append button causes the Snapshot to be saved to the first empty slot in the next Snapshot Bank. If there are no more empty Snapshot Slots, pressing the Append button causes nothing to happen. This would be the case when you have used up all 16 Snapshot Banks, each filled with 128 Snapshots.

Append

The Append button

#### **Inserting Snapshots**

You can also save the current Instrument settings as a new Snapshot that is inserted into the Snapshot List directly after the selected Snapshot. To do this, press the Insert button in the Snapshot List Operations area. Note that this can cause Snapshots to move from the current Bank to the next Bank.

Insert

The Insert button

#### **Overwriting Snapshots**

To replace the selected Snapshot with the current Instrument settings, use the Store button. Note that when you overwrite a Snapshot in this way, you lose its original settings.

Store

The Store button

Saving a "parent" Instrument's Snapshot saves the Snapshots of "child" Instruments as well, but only if the Snap Isolate checkbox in the respective Instrument's Function page is disengaged (see section 16.4.8, Defining Snapshot Behavior for Instruments for more information on this). Not only is the currently loaded "child" Instrument's Snapshot saved, but also the state of the Instrument's controls, even if a separate "child" Instrument Snapshot for that state doesn't exist.



The different areas of the Snapshot tab

## **Deleting Snapshots**

If you want to delete one or more Snapshots from the Snapshot List, select the Snapshots and either press the Del key on your computer keyboard or choose the *Delete selected Snapshots* menu entry from the Edit Bank drop-down menu, as shown in the figure below. Note that deleting Snapshots creates empty slots in the Snapshot List; you can use the *Sort and Compress Snapshots* entry from the Edit Bank drop-down menu to remove these gaps (see subsection  $\uparrow 6.4.7$ , Snapshot Banks).



The Delete selected Snapshots menu entry.

#### **Setting Instrument Settings to Default Values**

You can change the settings of all Instrument controls (which do not have the Snap Isolate checkbox engaged, see section  $\uparrow$ 6.4.1, Recalling Snapshots) to their default values. The Default value for a control is set with the Default edit field in the corresponding Module's Function page. You set the Instrument controls to their Default values by choosing the *Recall default values* menu entry (see figure below) from the Edit Bank drop-down menu. This changes the selected Snapshot's settings, but does not save the changed Snapshot. To do this, you must subsequently press the Store button.

Store

The Store button

Use the Set control values as default and Recall default values menu entries to set and recall default settings.



# **Setting Control Values as Default**

You can acquire the current settings of all of the Instrument's controls as the Default values to be used when the state of a control is to be reset. This is also the case when applying the *Recall default values* menu entry discussed above.

# 6.4.3 Renaming and Copying Snapshots

Since there are no explicit "rename" and "copy" operations in the Snapshot tab, these two common tasks will be explained in this section.

## **Renaming Snapshots**

There are two ways to rename an existing Snapshot in the Snapshot List:

- Double-click on the Snapshot and type the desired name. Then press the Enter key on your keyboard to save the renamed Snapshot.
- Alternatively, select the Snapshot and click on the Store button. Next you must type in the desired name and then click on the Store button once more to save the renamed Snapshot.

Store

### **Copying Snapshots**

As with renaming, there are two ways to copy Snapshots within the Snapshot List of an Instrument:

- For the first way select the Snapshot, then click on the Append button. Next rename the appended Snapshot if desired, and the click on the Append button a second time to save the appended Snapshot. Note that this copies that Snapshot to the first empty slot in the Snapshot List.
- You can also first select the Snapshot, then click on the Insert button. Following that, rename the inserted Snapshot if desired, and then click on the Insert button once more to save the inserted Snapshot. Note that this copies the Snapshot to a new slot below the originally selected slot in the Snapshot List.

Insert

Append

# 6.4.4 Comparing Snapshots

REAKTOR makes sound design easy for you by letting you compare a Snapshot with a modified version of the same Snapshot or with another, completely different Snapshot. This section describes how to do these two tasks. The basic idea behind the "Compare" feature is simple. The modified (or different) Snapshot is stored in the "compare buffer", and the *Compare Snapshot* menu entry is used to toggle between the original Snapshot and the modified (or different) Snapshot.

# Banks	Edit 🔻 🗮 🦳
Bank 1	New Bank
	Save Bank
	Load Bank
	Clone Bank
Snapshot Morphing + Rar	Init Bank
	Delete Bank 📃
1 - Nautic 1.00 8	Sort and Compress Snapshots
Dandamina 100	Delete selected Snapshots
Randomize 100 R	Compare Snapshot
# Snapshots	Set control values as disfault
001 Nautic	Recall default values
002 PAD Carbon Two	

The Compare Snapshot menu entry in the Edit Bank drop-down menu

# **Comparing an Original Snapshot with a Modified Version**

To compare a Snapshot with a modified version of the same Snapshot, follow these instructions:

- 1. Make sure you have an Instrument open.
- 2. Open the Snapshot tab.
- 3. Select a Snapshot in the Snapshot List.
- 4. Make sure there is no checkmark in fron of the *Compare Snapshot* menu entry in the Edit Bank drop-down menu.
- 5. Modify the settings of the Instrument controls as desired.
- 6. Use the *Compare Snapshot* menu entry in the Edit Bank drop-down menu to toggle between the original and modified Snapshot versions.
- 7. If you want to make further modifications, repeat instruction steps 5-6.

# **Comparing Two Different Snapshots**

To compare two different Snapshots in the Snapshot List of an Instrument, follow these instructions:

- 1. Make sure you have an Instrument open with at least two Snapshots.
- 2. Open the Snapshot tab.
- 3. Select a Snapshot in the Snapshot List.
- 4. Next, select another Snapshot in the Snapshot List. The first Snapshot is now stored in the "compare buffer".
- 5. Now you can use the Compare Snapshot menu entry in the Edit Bank drop-down menu (shown in the figure above) to toggle between the two Snapshots.



If you are modifying a Snapshot and accidentally select a different Snapshot, you can recover your modifications by clicking on the Compare button right away (before you make any changes to the new Snapshot).

# 6.4.5 Morphing between Snapshots

Not only can you compare two Snapshots, but you can even morph between them, that is, change an Instrument's Panel control settings gradually (over a time interval of [0 ... 60] seconds) from their values in one Snapshot to their values in another Snapshot. The Snapshot Morph area (see below), holds the controls for morphing between Snapshots.



The Snapshot Morph area in the Snapshot tab lets you morph between two Snapshots in the Snapshot List.

To morph between two Snapshots, follow these instructions:

- 1. Make sure you have an Instrument open with at least two Snapshots.
- 2. Open the Snapshot tab with the desired Snapshot List. If the Snapshot Morph area depicted in the figure above is not open, press the arrow button next to the text "Snapshot Morphing and Random", shown below.

Snapshot Morphing + Random				
#	Snapshots			
001	Nautic	-		
002	PAD Carbon Two			
003	CH When White is Yellow			
004	CH Come Take Me One			
005	CH Come Take Me Two			
006	CH Experienced			

3. Set your desired morphing time in seconds (a value in the interval [0...60]) in the Morph Time edit field. This value determines how long it will take the controls to morph (move) from their current settings to their new settings.



4. Next click on the Select A button to activate it (the text will change to "Select...").



5. Then select the first of the two Snapshots (Snapshot A) between which you want to morph from the Snapshot List.



- 6. Now click the Select B button to activate it (it is the button that lies symmetrically to the Select A button to the right).
- 7. Select the second of the two Snapshots (Snapshot B) from the Snapshot List.
- 8. Gradual, incremental change between two Snapshots is the basis of morphing. Because button and switch settings cannot be changed gradually, REAKTOR does not let you morph them. Therefore, before you begin to morph, you must decide whether to use the button and switch settings from Snapshot A or Snapshot B. To use the button and switch states from Snapshot A, press the State A button to the left of the Morph slider (see below). The button should light up. Alternatively, to use the button and switch states from Snapshot B, press the State B button to the right of the Morph slider (in this case this button should light up).



9. Now you are ready to morph between the two Snapshots. Move the horizontal Morph slider (see figure below) to a new position. When the slider is set fully to the left, the Instrument control settings (except perhaps the button states) correspond purely to Snapshot A. Similarly, when the slider is set fully to the right, the control settings correspond to Snapshot B. A slider setting right in the middle corresponds to an arithmetic average between the control settings of the two Snapshots, that is, 50 % of Snapshot A and 50 % of Snapshot B. Other slider settings have analogous results. After moving the Morph slider to a new

position, the Instrument's controls will move from their current settings to the settings specified by the new Morph slider position in a time interval of the number of seconds specified in the Morph Time edit field (see figure below).



Once you have configured the morph settings you can use the Morph slider to morph between two Snapshots.

Morphing a Snapshot of a "parent" Instrument morphs the controls of "child" Instruments as well, but only if the Snap Isolate checkbox in the respective "child" Instrument's Function page is disengaged (see section  $\uparrow$ 6.4.8, Defining Snapshot Behavior for Instruments for more information on this).



Shorter Morph Time values decrease the delay between changing the Morph slider position and having the Panel controls complete their morphs. Longer Morph Time values increase this delay.

#### Making a Control Immune to Morphing

You can specify which Panel controls should not be affected by "morph" operations. To make a control immune to Snapshot morphing, follow these instructions:

- 1. Double-click on the desired control like a knob, fader, list, or button.
- 2. This should have opened up the control's Properties View. Now click on the Function button.

FUNCTION

3. Engage the Mrph./Rnd Isolate checkbox in the Snapshots area of the control's Function page. Now the Morph slider will have no effect on that control.

Vrph/Rnd Isol.



To see how to assign a MIDI controller to the Morph function, please refer to the Application Reference.

# 6.4.6 Randomizing Snapshots

Probably the fastest way to create a new Snapshot is by using the Randomize or Random Merge buttons. The Snapshot Randomize area in the Snapshot tab (see figure below) holds the controls with which you can quickly create a new Snapshot with varying degrees of random deviation from the current Snapshot.

Randomize 100 Rnd. Merge

The Snapshot Randomize area in the Snapshot tab lets you create new Snapshots with varying degrees of random deviaton from the current Snapshot.

#### **Randomizing Snapshots**

If you want to randomize all of the selected Instrument's Panel controls (except those with the Random Isolate checkbox engaged, see below) follow these instructions:

- 1. Make sure you have an Instrument open.
- 2. Open the Snapshot tab and if the Snapshot Randomize area depicted above is not open, press the arrow button next to the text "Snapshot Morphing and Random", shown below.



3. First, decide what maximum amount of random deviation from the Instrument's current Panel controls you would like. Then enter the corresponding value into the Random Amount edit field. The Random Amount edit field accepts values in the range [0 ... 100]. "0" corresponds to 0 % and "100" corresponds to 100 % of the control's range. If we say the value in the Random Amount field is "R" then pressing the Randomize button can change the control's current setting up to  $\pm R$  % of the control's range. For example, if a knob with a range [-1 ... 1] is set to its middle point "0" and the Random Amount edit field is set to "25" (meaning 25 %), then clicking on the Randomize button can change the knob's value to anywhere from -0.5 to 0.5, that is,  $(0 \pm 0.25 * 2)$ . Note that a control can never be randomized to a value beyond its range:

Randomize	100	Rnd. Merge
-----------	-----	------------

4. After having entered the desired value into the Random Amount edit field, click on the Randomize button:



#### **Random Merging of Two Snapshots**

You can also use two existing Snapshots as seeds and randomly merge these two "parent" Snapshots to create a "child" Snapshot. The resulting "child" Snapshot is a random combination of the two "parent" Snapshots with the amount of randomness being set with the Random Amount edit field. To use this feature, you need to follow these instructions:

1. Make sure you have an Instrument open with at least two Snapshots.

Randomize	100	Rnd. Merge
-----------	-----	------------

2. Open the Snapshot tab and if the Snapshot Randomize area depicted above is not open, press the arrow button next to the text "Snapshot Morphing and Random", shown below.

Snapshot Morphing + Random			
#	Snapshots		
001	Nautic	4	
002	PAD Carbon Two		
003	CH When White is Yellow		
004	CH Come Take Me One		
005	CH Come Take Me Two		
006	CH Experienced		

- 3. You need to choose the first "parent" Snapshot. For that, click on the Select A button to activate it (its text should change to "Select...").
- 4. Then select the first of the two "parent" Snapshots (Snapshot A) from the Snapshot List.
- 5. Now click the Select B button to activate it (its text should change to "Select...").
- 6. Select the second of the two "parent" Snapshots (Snapshot B) from the Snapshot List.

7. To decide, what value you want to enter into the Random Amount edit field, consider the behavior of the "Random Merge" feature. The "Random Merge" operation is taken for each Instrument Panel control separately. Let's look at one control and let the value in the Random Amount edit field be denoted by the letter "R" (it is a value in the range [0 ... 100]). For an R = 0, pressing the Random Merge button results in the control receiving a new value that is exactly between the two values corresponding to the "parent" Snapshots. For R = 100, pressing the Random Merge button results in the control receiving either the value of "parent" Snapshot A or "parent" Snapshot B. In general, if R > 0, then pressing the Random Merge button causes the control randomly to be assigned to one of the two parents and the value "R" decides how much the new value of the control deviates from the perfect merge (arithmetic mean) of the two "parent" Snapshots in the direction of the assigned "parent" Snapshot. As mentioned above, for R = 100, the deviation is complete, that is, the new control value is that of the assigned "parent" Snapshot. Enter the value corresponding to the desired randomness into the Random Amount edit field.



8. Last, press the Random Merge button.

## Making a Control Immune to Randomization

You can specify which Panel controls should not be affected by "randomize" operations. To make a control immune to randomization, follow these instructions:

- 1. Double-click on the desired control like a knob, fader, list, or button.
- 2. This should have opened up the control's Properties View. Now click on the Function button.

FUNCTION

3. Engage the Mrph./Rnd Isolate checkbox in the Snapshots area of the control's Function page. Now the Randomize button will have no effect on that control. You can use this technique in conjunction with the Random Amount value to limit the amount of randomization an Instrument's controls receive.

Vrph/Rnd Isol.

The Mrph./Rnd Isolate checkbox
### 6.4.7 Snapshot Banks

Each and every Snapshot in REAKTOR belongs to a Snapshot Bank. You can save your Snapshots on your hard drive or any other medium and even share your Snapshots by saving the Snapshots Bank to which those Snapshots belong to. In this section you will learn all about Snapshot Banks in REAKTOR.

#### Saving, Loading, and Creating Snapshot Banks

This subsection will discuss the basic operations tied to Snapshot Banks.

#### **Selecting Snapshot Banks**

Some Instruments already come with several Snapshot Banks. To see which banks have already been loaded and to select a new bank, follow these instructions:

- 1. First, open an Instrument that has several Snapshot Banks already loaded. Space Drone is a good example of one, you can find it in the factory library in under New Additions > Sound Generators.
- 2. Open the Snapshot tab and look at the Snapshot Banks area shown in the figure below.



3. As you can see in the figure above, two banks have been loaded. Click on Bank 2 to load the second Snapshot Bank into the Snapshot List.

#### Saving and Loading Snapshot Banks

To save a Snapshot Bank, follow these steps:

- 1. Make sure you have an Instrument open.
- 2. Open the Snapshot tab and look at the Snapshot Banks area shown in the figure below.



- 3. To save the selected Snapshot Bank (see above), click on the Edit Bank drop-down menu and choose the *Save Bank* menu entry. This will open a dialog box to choose where you want to save the Snapshot Bank file. The Snapshot Bank file is saved as an \*.ssf file.
- 4. To load a new Snapshot Bank into REAKTOR, choose the *Load Bank* menu entry from the Edit Bank drop-down menu, as shown in the figure below. This will open a dialog box to browse for the \*.ssf Snapshot Bank file you wish to load.

SpaceDrone -	Linked
# Banks	
001 Bank 1	New Bank
002 Bank 2	Save Bank
	Load Bank
	Clone Bank
Snapshot Morphing + Ran	Init Bank
	Delete Bank
1: 14 - Drip 1.00 1:	Sort and Compress Snapshots
Dandamine 100 D	Delete selected Snapshots
Kandomize 100 K	Compare Snapshot
# Snapshots	Set control values as default
001 Martians!	Recall default values
002 Tibet	

- 5. After clicking on "OK" in the dialog box, the Snapshots contained in the Snapshot file you just loaded are appended to the current Snapshot List. If the list is full, then a new Snapshot Bank is created and the remaining Snapshots from the Snapshot file are loaded into that new Bank.
- 6. Usually one creates a new Bank right away before loading the Snapshots that are in a file into the Bank. This way the Snapshots in different Banks and Snapshot files don't get mixed up. To create a new Bank, click on the Edit Bank drop-down menu and choose the New Bank menu entry. This creates a new Snapshot Bank consisting of empty slots. You can now either start creating and saving your own Snapshots with the Instrument (see section ↑6.4.2, Adding and Removing Snapshots) or load the Snapshots from a Snapshot Bank file into the Bank as shown in steps 4 and 5.

# Banks	
001 Bank 1	New Bank
002 Bank 2	Save Bank
<ul> <li>Snapshot Morphing + Ran</li> </ul>	Clone Bank Init Bank Delete Bank
1: 14 - Drip 1.00 1:	Sort and Compress Snapshots
Randomize 100 R	Delete selected Snapshots Compare Snapshot
# Snapshots 001 Martians!	Set control values as default Recall default values
002 Tibet	

To create a new Snapshot Bank, select the New Bank menu entry from the Edit Bank drop-down menu.

#### **Cloning and Deleting Banks**

This subsection describes how to clone (duplicate), init (clear all Snapshots), and delete Snapshot Banks.

Cloning Banks can be useful in many cases. Maybe you want to duplicate a factory Snapshot Bank to create your own modifications to the Snapshots or perhaps you want to use the duplicate Bank to pick out only Snapshots that have a certain flavor to them. This is how you clone a Bank:

- 1. Make sure you have an Instrument open.
- 2. Open the Snapshot tab and click on the Edit Bank drop-down menu.
- 3. Click on the *Clone Bank* menu entry (see below). A new Snapshot Bank will be created with its Snapshot List identical to the Bank that you cloned.



4. To clear all Snapshots from the currently selected Bank and replace them with empty slots, you need to click the *Init Bank* menu entry (see below).

# Banks	
001 Bank 1	New Bank
002 Bank 2	Save Bank
	Load Bank
	Clone Bank
Snapshot Morphing + Rar	Init Bank
	Delete Bank 😽
1: 5 - Polar 1 1.00 1:	Sort and Compress Snapshots
Randomize 100 R	Delete selected Snapshots Compare Snapshot
# Snapshots	Set control values as default
001 Sub Wind	Recall default values
002 Cave	

5. This results in an empty Snapshot Bank (see figure below). And if you want to delete a Snapshot Bank completely, choose the *Delete Bank* menu entry from the Edit Bank dropdown menu. Note that you cannot delete a Snapshot Bank if it's the only one left for that Instrument.

001	
002	
003	
004	
005	
006	
007	
008	
009	

If you delete a Bank by mistake, don't panic! Simply use REAKTOR's *Undo Delete Snap Bank* menu entry in the *Edit* application menu to restore it.

#### **Renumbering and Renaming Banks**

Let's say you want to take a factory Snapshot Bank, remove the Snapshots you don't like, and rename the new Bank. In this subsection you will first learn how to get rid of the gaps in the Bank that result from deleting Snapshots by using the "Renumber Bank" feature. Then you will see how to rename your Bank. Perform the following steps:

1. Make sure you have an Instrument open.

- 2. Now open the Snapshot tab and clone a Bank so that you don't lose the Snapshots you are about to delete in the cloned Bank (see subsection ↑6.4.7, Snapshot Banks on how to clone Banks).
- 3. Next, delete some Snapshots from the cloned Snapshot Bank by selecting the Snapshot Entry and then choosing the *Delete Snapshot* menu entry from the *Edit Bank* drop-down menu. You can also use the [Del] key on your computer keyboard. The resulting Snapshot List should look something like the one shown below.



→ Deleted Snapshots are replaced by Snapshot entries labeled <empty>:



#### **Resorting the Snapshot List**

Now resort the Snapshot List by shifting the Snapshots upwards so that there are no empty slots between individual Snapshots:

1. Click on the Edit Bank drop-down menu and select the *Sort and Compress Snapshots* menu entry (see figure below).

#	Banks	Edit 🔻	2	CARBC
001	Bank 1	New Ba	nk	
		Save Bank		
		Load Ba	nk	
		Clone Ba	nk	Γ
● s	napshot Morphing + Rar	Init Banl	k	
	Spanchote	Delete B	lank	
	Shapshots	Sort and	Compres	ss Snapshots
001		Delete s	enscted Si	napshots 🛛 🗸
002	Sonntagsgeraeusch	Compare	e Snapsho	ot L
003	SOME SOME things	Catarant		an defeult
004		Set control values as default		as default
005	The Combsong	Recall de	erault val	ues
006				

2. The resulting Snapshot List should now look similar to the one shown below.



After selecting the Sort and Compress Snapshots menu entry from the Edit Bank drop-down menu all empty slots in the Snapshots List are removed.

#### **Renaming a New Snapshot List**

► To rename the Bank that is your new Snapshot List, type the new name into the Bank Name edit field, as shown below.



#### 6.4.8 Defining Snapshot Behavior for Instruments

In Ensembles consisting of several Instruments, Snapshots of one Instrument often go together with particular Snapshots of another Instrument. Junatik is an example of such an Ensemble: it consists of a synthesizer Instrument and a delay effect Instrument. Therefore it is often desirable to recall or save the Snapshots for several Instruments simultaneously. You can also specify other specifics regarding Snapshot behavior of Instruments. This section discusses all things connected to an Instrument's behavior regarding Snapshots. The picture below shows the Snapshot area of an Instrument's Function Tab where the properties of its Snapshot behavior are set.



An Instrument's Snapshot behavior is determined by the settings in the Snapshot area of the Instrument's Function page.

#### **Instruments Hierarchy**

Any Instrument that contains another Instrument is called a "parent" Instrument. For example, an Ensemble (top-level Instrument) that contains another Instrument is a "parent" Instrument. A "child" Instrument is an Instrument that is contained within another ("parent") Instrument. It is important to understand this hierarchy in order to properly control the Snapshot Behavior.

#### The Snap Isolate Property

By default, Snapshots are stored and recalled by the "parent" Instrument (usually the Ensemble). This means that you can store and recall Snapshots for multiple "child" Instruments at the same time using the "parent" Snapshot. Sometimes this is just what you want. Other times, you might want to store and recall Snapshots independently of the "parent" Instrument. This is done using the Snap Isolate property, as shown by the instruction steps below.

- 1. Open or create an Ensemble containing two Instruments, each with its own populated Snapshot List.
- 2. Go to the Function page of both "child" Instruments and make sure that the Snap Isolate checkbox is disengaged, as shown in the figure below. This means that Snapshot recall, store, and morph operations done on the Ensemble will effect the "child" Instruments. Let's see what this means.



- 3. First change the state of the controls of the "child" Instruments by recalling some other Instrument Snapshots.
- Now, store a new Snapshot for the Ensemble ("parent" Instrument). Please refer to section ↑6.4.2, Adding and Removing Snapshots if you don't know how to do this. Take note of which Instrument Snapshots are loaded during the storing process.
- 5. Again, change the state of the controls of the "child" Instruments by recalling some other Instrument Snapshots.
- 6. Next, recall the Ensemble Snapshot you stored last. Notice how the "child" Instruments automatically recalled the Snapshots that were loaded at the time when you saved the "parent" Snapshot.
- 7. What happens if we modify Instrument Snapshots and then store the Ensemble Snapshot? To see this, load some Instrument Snapshots and modify the Panel controls. Note that an asterisk appears in the Snapshot drop-down menu in the Instrument header when a Snapshot has been modified. This is shown in the figure below.

* 1·1 - Sonntagegeraeusch	
n i sonnagsgeraeusen	

- 8. Append another Ensemble ("parent" Instrument) Snapshot.
- 9. Modify the Instrument controls

- 10. Recall the Ensemble Snapshot you just saved. Notice how not only the Instrument Snapshots were recalled, but also the modifications that you did to the Instrument controls. Because the Instrument controls have been modified from their Snapshot values by the Ensemble Snapshot, the asterisk again appears in the Instrument header, as shown above.
- 11. Now, let's see what happens if the Snap Isolate checkbox is engaged. Go to the Function pages of the "child" Instruments and engage the Snap Isolate checkbox, as shown in the figure below.



- 12. Now append yet another Ensemble Snapshot.
- 13. Now change the state of the controls of the "child" Instruments by recalling some other Instrument Snapshots.
- 14. Next, recall the Ensemble Snapshot you just stored. Notice how the Instrument's controls or the Instrument Snapshots remain unchanged upon the Ensemble Snapshot recall. This is exactly what the effect of engaging the Snap Isolate checkbox is.

In summary, when you recall the Snapshot of a "parent" Instrument, the Snapshots of all "child" Instruments which have the Snap Isolate checkbox in their Function page disengaged, will also be recalled. Similarly, saving a new Snapshot for the "parent" Instrument saves the Snapshots of its "child" Instruments which have the Snap Isolate checkbox disengaged. Note that recalling a "parent" Instrument Snapshot not only recalls the "child" Instrument's Snapshot that was loaded at the time of storing the "parent" Snapshot, but also sets the "child" Instrument's controls to the state in which the "parent" Snapshot was stored.



Generally you can have an Ensemble containing both Snap Isolated and non-Snap Isolated "child" Instruments.

The "parent" Instrument must not necessarily be the Ensemble. It can be any Instrument that contains another Instrument. If a non-Snap Isolated Instrument contains another non-Snap Isolated Instrument, then changing the Ensemble Snapshot will affect the "child" Instruments all the way down to the lowest level of the Instrument hierarchy.

#### **The Snapshot Master**

The Snapshot Master feature is particularly relevant when running REAKTOR as a plug-in. When this feature is activated for an Instrument or Ensemble, the Snapshots List of that Instrument is forwarded to the host. It also appears in the Snapshot menu in the Main Toolbar. However, since most hosts can handle only one Snapshots List, this feature can be enabled for only one Instrument (or the Ensemble). This is done using the Set As Master button, as shown by the instruction steps below.

- 1. Make sure you have an Ensemble with two active Instruments open.
- 2. First you need to choose which Instrument is the Snapshot Master for your Ensemble. By default, the Snapshot Master is the Ensemble. To set an Instrument to be the Snapshot Master Instrument, go to the Function page of the Instrument Properties, as shown below.



3. Then engage the Set As Master button. When the Set As Master button is engaged, the Instrument's Snapshots are available in the host program and appear in the Snapshot menu in the Main Toolbar. Note that an icon appears in the Snapshot drop-down menu in the Instrument header to show it is now the Snapshot Master.

📃 30 - Spooky Resonance

#### **Recalling Snapshots by MIDI**

Each Snapshot Bank can hold 128 Snapshots. This number is not arbitrary; it has been chosen to provide optimal compatibility when recalling Snapshots via MIDI Program Change messages. To enable the Recall by MIDI option, engage the Recall by MIDI checkbox in the Instrument's Function page.

#### 🗸 Recall by MIDI

The Recall by MIDI checkbox

When the Recall by MIDI checkbox has been engaged, an incoming MIDI Program Change message with the value "N" (where "N" is an integer in the range [0...127]) will recall the Snapshot with the number "N + 1" (if that Snapshot exists). Thus a Program Change message of "0" will recall Snapshot "1", a message of "1" will recall Snapshot "2", and so on. This

way you can quickly and easily recall Snapshots from your MIDI device by issuing MIDI Program Change messages for the desired Snapshot number. If the "parent" Instrument also has this feature enabled and is on the same MIDI channel as another "child" Instrument, then the "parent" Instrument's Snapshot will take precedence. Please refer to subsection 13.2.1 in the Application Reference to learn how to change the incoming MIDI channel number for an Instrument.

### 6.4.9 Opening and Saving Presets

REAKTOR 5.6.2 allows you to quickly save and recall the complete state of an existing Ensemble using the new Preset file. The extension of the REAKTOR Preset file is \*.nrkt.

#### Saving a Preset File

To save a Preset file, follow these instructions:

- 1. Open the Ensemble for which you wish to save a Preset.
- 2. If your Ensemble contains "child" Instruments for which you wish the Preset file to save the control settings, make sure that the Snap Isolate checkbox in the respective Instrument's Function page is disengaged (see section ↑6.4.8, Defining Snapshot Behavior for Instruments for more information on this).
- 3. Press the Menu button and choose the *File > Save Preset As...* menu entry (shown in the figure below).



Use the File > Save Preset As... menu entry to save a Preset file.

Note that the Preset file does not contain the Ensemble itself. It merely stores the Ensemble location. Therefore, if you modify the Ensemble or change the Ensemble's location you will not be able to recall the Preset!

#### Loading a Preset File

To load a Preset file, follow these instructions:

Press the Menu button and choose the File > Open Preset menu entry (shown in the figure below).



Use the File > Open Preset menu entry to load a Preset file.

Note that the Preset file does not contain the Ensemble itself. It merely stores the Ensemble location. Therefore, if you modify the Ensemble or change the Ensemble's location you will not be able to recall the Preset!



If you are already familiar with the REAKTOR 5.5 Snapshot behavior and are just interested in the changes, you may use the cross-reference link to proceed on to section  $\uparrow$ 6.4.8, Defining Snapshot Behavior for Instruments.

## 7 Keyboard Shortcuts

### 7.1 Changed Keyboard Shortcuts

In REAKTOR 5.6.2, the following keyboard shortcuts have changed:

- Toggle Edit mode: [F1]
- Toggle Horizontal Split Pane: [F2]
- Toggle Vertical Split Pane: [F3]
- Toggle Properties View: [F4]

## 7.2 New keyboard Shortcuts

In REAKTOR 5.7, the following keyboard shortcuts have been added:

- Close a Pane or Screenset: [Ctrl] + [F4] ([Cmd] + [W] on Mac)
- Create a new Screenset: [Ctrl] + [T] ([Cmd] + [T] on Mac)
- Switch to next Screenset: [Ctrl] + [Tab]
- Switch to previous Screenset: [Ctrl] + [Shift] + [Tab]
- Select Screenset: [Ctrl] + [Alt] + [1...8] ([Ctrl] + [Cmd] + [1...8] on Mac)
- Enable/Disable Wire Debugging: [Ctrl] + [B] ( [Cmd] + [B] on Mac)

In REAKTOR 5.6.2, the following keyboard shortcuts have been added:

- Scrolling of the Structure: [Alt] + Drag
- Navigate the the previous Structure: [Alt] +[B]
- Show the contents of a Macro in the other Split Pane: [Alt] + double-click Macro
- Open the Searchbox: [Enter]/[Return] or [Ctrl] +[F] in Windows ([Cmd] +[F] in Mac OS X)
- Navigate to the parent folder in the Browser's folder tree: Left Arrow

- Delete Objects and Wires: [Backspace] or [Delete]
- Duplicate Objects: [Ctrl] + drag Object ([Alt] + drag on Mac OS X)
- Copy Objects to the other Split Pane: [Ctrl] + drag ([Alt] + drag on OS X)
- Breadcrumb Navigation, down: [Alt] + [Right]
- Breadcrumb Navigation, up: [Alt] + [Left]

# 8 Keyboard Shortcut Overview

APPLICATION	Action	Mac OS X	Windows
	Show module search box	[Enter], [Cmd] + [F]	[Enter], [Ctrl] + [F]
	Preset change (when an instrument is selected)	[Up], [Down]	[Up], [Down]
	View Info	[Cmd] + [I]	[Ctrl] + [I]
	Toggle MIDI & OSC Learn	[Cmd] + [M]	[Ctrl] + [M]
	Toggle Audio	[Cmd] + [R]	[Ctrl] + [R]
	Start Clock	[Space]	[Space]
	Reset Clock	[Cmd] + [Space]	[Ctrl] + [Space]
	Preferences	[Cmd] + [,]	[Ctrl] + [,]
	Quit	[Cmd] + [Q]	[Alt] + [F4]
FILE	Action	Mac OS X	Windows
	New	[Cmd] + [N]	[Ctrl] + [N]

Open	[Cmd] + [0]	[Ctrl] + [O]
Save	[Cmd] + [S]	[Ctrl] + [S]
Save As	[Cmd] + [Shift] + [S]	[Ctrl] + [Shift] + [S]
Action	Mac OS X	Windows
Undo	[Cmd] + [Z]	[Ctrl] + [Z]
Redo	[Cmd] + [Y]	[Ctrl] + [Y]
Select All in Structure	[Cmd] + [A]	[Ctrl] + [A]
Marquee Select	Click and drag around a group	Click and drag around a group
Add To or Remove From Selection	[Cmd] + Click	[Ctrl] + Click
Cut	[Cmd] + [X]	[Ctrl] + [X]
Сору	[Cmd] + [C]	[Ctrl] + [C]
Paste	[Cmd] + [V]	[Ctrl] + [V]
Duplicate	[Cmd] + [D]	[Ctrl] + [D]
Duplicate (In Structure)	[Alt] + drag Module	[Ctrl] + drag Module

EDIT

	Delete	[Delete]	[Backspace], [Delete]
SNAPSHOT	Action	Mac OS X	Windows
	Next Master Snapshot	[Cmd] + [Down]	[Ctrl] + [Down]
	Prior Master Snapshot	[Cmd] + [Up]	[Ctrl] + [Up]
PANEL	Action	Mac OS X	Windows
	Toggle Panel Edit	[Cmd] + [P]	[Ctrl] + [P]
	Save Panelset 18	[Cmd] + [Shift] + [1	[Ctrl] + [Shift] + [18]
		8]	
VIEW	Action	8] Mac OS X	Windows
VIEW	Action Append Screenset	8] <b>Mac OS X</b> [Cmd] + [T]	Windows [Ctrl] + [T]
VIEW	Action Append Screenset Recall Screenset 18	8] <b>Mac OS X</b> [Cmd] + [T] [Cmd] + [18]	Windows [Ctrl] + [T] [Ctrl] + [18]
VIEW	Action Append Screenset Recall Screenset 18 Next Screenset	8] <b>Mac OS X</b> [Cmd] + [T] [Cmd] + [18] [Ctrl] + [Tab]	Windows [Ctrl] + [T] [Ctrl] + [18] [Ctrl] + [Tab]
VIEW	Action Append Screenset Recall Screenset 18 Next Screenset Previous Screenset	8] <b>Mac OS X</b> [Cmd] + [T] [Cmd] + [18] [Ctrl] + [Tab] [Ctrl] + [Shift] + [Tab]	Windows [Ctrl] + [T] [Ctrl] + [18] [Ctrl] + [Tab] [Ctrl] + [Shift] + [Tab]

Forward in Bread Crumbs (Structure View)	[Alt] + [Right]	[Alt] + [Right]
Backward in Bread Crumbs (Structure View)	[Alt] + [Left]	[Alt] + [Left]
Toggle Horizontal View Button	[F2]	[F2]
Toggle Vertical View Button	[F3]	[F3]
Switch Between Horizontal and Verti- al View (Structure View)	[Ctrl] + [H]	[Ctrl] + [H]
Close Pane / Screenset	[Cmd] + [W]	[Ctrl] + [F4]
Scroll	[Alt] + drag background	[Alt] + drag back- ground
Scroll Toggle Properties	[Alt] + drag background [F4]	[Alt] + drag back- ground [F4]
Scroll Toggle Properties Toggle Browser	[Alt] + drag background [F4] [F5]	[Alt] + drag back- ground [F4] [F5]
Scroll Toggle Properties Toggle Browser Toggle Snapshots	[Alt] + drag background [F4] [F5] [F6]	[Alt] + drag back- ground [F4] [F5] [F6]
Scroll Toggle Properties Toggle Browser Toggle Snapshots Toggle Panelsets	[Alt] + drag background [F4] [F5] [F6] [F7]	[Alt] + drag back- ground [F4] [F5] [F6] [F7]
Scroll Toggle Properties Toggle Browser Toggle Snapshots Toggle Panelsets Toggle Sample Map Editor	[Alt] + drag background [F4] [F5] [F6] [F7] [F9]	[Alt] + drag back- ground [F4] [F5] [F6] [F7] [F9]

	Full Screen Mode	[F11]	[F11]
	Show Structure in Other Pane	[Alt] + Double-click	[Alt] + Double-click
	Back / Previous structure	[Alt] + [B]	[Alt] + [B]
DEBUG STRUCTURE	Action	Mac OS X	Windows
	Enable Wire Debugging	[Cmd] + [B]	[Ctrl] + [B]
	Measure CPU Usage	[Cmd] + [U]	[Ctrl] + [U]
	Toggle relative/absolute CPU usage (when <i>measure CPU usage</i> option is active)	[Cmd] + Click in pri- mary structure back- ground	[Ctrl] + Click primary structure background
	Show Module Sorting	[Cmd] + [Alt] + [A]	[Ctrl] + [Alt] + [A]
	Show Event Init Order	[Cmd] + [Alt] + [E]	[Ctrl] + [Alt] + [E]